
PHILIPS
ADVANCE

H-1Q26-TP-BLS	
Brand Name	**COMPACT-HPF**
Ballast Type	**Magnetic**
Starting Method	**Pre-Heat**
Lamp Connection	**Series**
Input Voltage	**120**
Input Frequency	**60 HZ**
Status	**Active**

Electrical Specifications

Lamp Type	Num. of Lamps	Rated Lamp Watts	Min. Start Temp (°F/C)	Input Current (Amps)	Starting Current (Amps)	Open Circuit (Amps)	Input Power (Watts)	Ballast Factor	MAX THD %	Power Factor
* CFM26W/GX24D	1	26	50/10	0.24	0.33	0.41	28	0.85	25	0.97
CFQ26W/G24D	1	26	50/10	0.24	0.33	0.41	28	0.83	20	0.99
CFS21W/GR10Q	1	21	25/-04	0.23	0.33	0.41	26	0.82	15	0.95
CFS28W/GR8	1	28	25/-04	0.24	0.33	0.41	27	0.80	20	0.99

Wiring Diagram



Diag. 47


The wiring diagram that appears above is for the lamp type denoted by the asterisk (*)

Standard Lead Length (inches)

	in.	cm.
Black		
White	7	
Blue	7	
Red		
Yellow		
Gray		
Violet		

	in.	cm.
Yellow/Blue		
Blue/White		
Brown		
Orange		
Orange/Black		
Black/White	7	
Red/White		

Enclosure



CASE "T"

Enclosure Dimensions

OverAll (L)	Width (std)/(TP)	Height (H)	Mounting (M)
6.5 "	2.375 "	1.5 "	6.0 "
6 1/2	2 3/8	1 1/2	6
16.5 cm	6 cm / 0 cm	3.8 cm	15.2 cm

Revised 06/29/99

Data is based upon tests performed by Philips Lighting N.A in a controlled environment and representative of relative performance. Actual performance can vary depending on operating conditions. Specifications are subject to change without notice. All specifications are nominal unless otherwise noted.

Philips Lighting Electronic N.A
10275 West Higgins Road Rosemont, IL 60018 Tel.: 800-322-2086 Fax: 888-432-1882
Customer Support/Technical Service: 800-372-3331 · OEM Support: 866-915-5886