



# Theta FBS110

# FBS115 MAX18W-E27 220-240V

## E27, 220 to 240 V

Our Smart CFL-I downlight is a safe, reliable and flexible solution that comes in five sizes for different cut-outs. Its elegant design guarantees a perfect fit in any retail or hospitality environment. And because the downlight has been designed specifically for CFL-I lamps, installation and maintenance couldn't be any simpler.


#### **Product data**


General Information		
Cap-Base	E27 [E27]	
Gear	-	
Lighting Technology	LED	
Light Technical		
Number of light sources	1	
Luminaire light beam spread	108°	
Operating and Electrical		
Input Voltage	220 to 240 V	
Line Frequency	50 Hz	
Input Frequency	50 Hz	
Temperature		
Ambient temperature range	-10 to +35 °C	
Mechanical and Housing		
Housing Color	White	
Overall length	85 mm	
Overall width	300 mm	


Overall height	300 mm	
Dimensions (Height x Width x Depth)	300 x 300 x 85 mm	
Approval and Application		
Ingress protection code	IP20 [Finger-protected]	
Mech. impact protection code	IK03 [0.3 J]	
Protection class IEC	Safety class II	
Product Data		
Order product name	FBS115 MAX18W-E27 220-240V	
Full product name	FBS115 MAX18W-E27 220-240V	
Full product code	910403630467	
Order code	910403630467	
Material Nr. (12NC)	910403630467	
Numerator - Quantity Per Pack	1	
EAN/UPC - Product/Case	8710163289007	
Numerator - Packs per outer box	12	
EAN/UPC - Case	8710163289052	

## Theta FBS110

### Dimensional drawing









© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.

www.lighting.philips.com 2023, April 29 - data subject to change