



Core & Coil (71A) MH ~GT~ 450W

CORE & COIL HID MH BAL 1000W M47 5-TAP KIT (ALL CU)

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

| General Information | |
|------------------------------|--------------------|
| ANSI Code | M47 |
| Lamp Type | 1000W MH |
| Number of Lamps | 1 piece/unit |
| Circuit Type | CWA |
| Ballast Type | Magnetic HID |
| Base Model | 71A6552CU |
| Core Size | 4 1/4 x 6 (2 Coil) |
| Suitable For Outdoor Use | Yes |
| Ignitor Catalog Number | NA |
| Ignitor Temperature Rating | NA |
| Capacitor Value | 24 MFD |
| Capacitor Catalog Number | MD2409000 |
| Capacitor Requirements | 480V |
| Capacitor Temperature Rating | 90℃ |
| Capacitor Diameter/Oval | 1.75 in |
| Dimensions | |
| Capacitor Height | 3.90 in |
| Automatic Restart | No |
| | |

| Operating and Electrical | | | | | | |
|-------------------------------|---|--|--|--|--|--|
| Input Voltage | 120/208/240/277/480 V | | | | | |
| Input Frequency | 60 Hz | | | | | |
| Inp. Current (Open Circuit) | 5.16/4.3/3.09/2.61/1.6 A | | | | | |
| Input Current (Starting) | 6/2.82/3/2.3/1.53 A | | | | | |
| Input Current (Short Circuit) | 4.35-6.52/2.16-3.24/2.04-3.06/1.8-2.71/1-1.51 V | | | | | |
| Secondary Short Circuit | 4.97-6.08 A | | | | | |
| Current | | | | | | |
| Constant Wattage Deviation | 10% | | | | | |
| Ballast Factor (Nom) | 1 | | | | | |
| Power Factor (Nom) | 0.90 | | | | | |
| Nominal Open Circuit Voltage | 426 V | | | | | |
| Input Current (Operating) | 9.05/5.6/4.7/4.07/2.36 A A | | | | | |
| (Nom) | | | | | | |
| Input Power (Nom) | 1080 W | | | | | |
| Rated Lamp Watts | 1000 W | | | | | |
| | | | | | | |
| Wiring | | | | | | |
| Wire Striplength | 0.5 mm | | | | | |
| Wire Length by Color | 12" | | | | | |


Datasheet, 2019, March 22 data subject to change

Core & Coil (71A) MH ~GT~ 450W

| Wire Type | Stranded | | | | | |
|-----------------------------|------------------------------------|--|--|--|--|--|
| Remote Wiring Configuration | Yes | | | | | |
| Allowed | | | | | | |
| Max Ballast-Lamp Distance | Determined by AWG used | | | | | |
| Remote Wiring | | | | | | |
| Recommended Fuse Value | 22/15/12/10/6 A | | | | | |
| | | | | | | |
| Approval and Application | | | | | | |
| Open Circuit Voltage Test | 383-468 V | | | | | |
| (Volts) | | | | | | |
| Approbation Marks | ULR CSA certificate RoHS Compliant | | | | | |
| Temperature Marking | D/D/C/C/C | | | | | |
| UL Recognized | Yes | | | | | |
| Hipot Test (1 Minute) | 2000 V | | | | | |
| Hipot Test (2 Seconds) | 2500 V | | | | | |

| 9D RE & COIL HID MH BAL 1000W M47 5-TAP KIT (ALL |
|---|
| RE & COIL HID MH BAL 1000W M47 5-TAP KIT (ALL |
| · |
| · |
| · |
| |
| 097009159 |
| 367096136 |
| 6552001CU |
| |
| |
| |
| 701146201 |
| 66 kg |
| |

Dimensional drawing



MH BAL 1000W M47 5-TAP KIT (ALL CU)

| Product | C1 | C2 | A1 | A2 | А3 | B1 | B2 |
|------------------------------|---------|------|------|--------|--------|--------|--------|
| CORE & COIL HID MH BAL 1000W | 4.70 in | 3 in | 6 in | 5.4 in | 4.4 in | 4.3 in | 3.9 in |
| M47 5-TAP KIT (ALL CU) | | | | | | | |

