
PHILIPS ADVANCE

High Pressure Sodium Lamp Ballast

Catalog Number 71A7907B
For 70W S62
60 Hz R-HPF
Status: Active

DIMENSIONS AND DATA

2 5/8 X 2 3/16 CORE



INPUT VOLTS		120				
CIRCUIT TYPE	R-HPF					
POWER FACTOR (min)	90%					
REGULATION						
Line Volts	±5%					
Lamp Watts	WITHIN TRAPEZOID					
LINE CURRENT (Amps)						
Operating		0.75				
Open Circuit		1.30				
Starting		0.90				
UL TEMPERATURE RATINGS						
Insulation Class	H(180℃)					
Coil Temperature Code	1029	A				
MIN. AMBIENT STARTING TEMP.	-40℉ or -40℃					
NOM. OPEN CIRCUIT VOLTAGE	120					
INPUT VOLTAGE AT LAMP DROPOUT		96				
INPUT WATTS	86					
RECOMMENDED FUSE (Amps)		3				
CORE and COIL						
Dimension (A)	1.30					
Dimension (B)	2.90					
Weight (lbs.)	2					
Lead Lengths	12"					
CAPACITOR REQUIREMENT						
Microfarads	28.0					
Volts (min.)	120					
Fault Current Withstand (amps)						
60 Hz TEST PROCEDURES (Refer to Advance Test Procedure for HID Ballasts - Form 1270)						
High Potential Test (Volts)						
1 minute	2000					
2 seconds	2500					
Open Circuit Voltage Test (Volts)	114-126					
Short-Circuit Current Test (Amps)						
Secondary Current	1.90-2.90					
Input Current		0.65-1.05	-	-	-	-

Capacitor: 7C280M12RA



Capacitance: 28
Dia/Oval Dim: 1.65
Height: 2.75
Temp Rating: 105℃

Wiring Diagram:




Fig. H

Ignitor: INTEGRAL

An ignitor integral to the core and coil assembly is used to start the lamp.

Ballast to Lamp Distance (BTL) = 2 feet
Temp Rating: 125℃

Ordering Information

Order Suffix	Description

Data is based upon tests performed by Philips Lighting Electronic N.A. in a controlled environment and representitive of relative performance. Actual performance can vary depending on operating conditions. Specifications are subject to change without notice.

Philips Lighting Electronic N.A.
10275 West Higgins Road · Rosemont, IL 60018 · Tel:800-322-2086 Fax:888-432-1882
Customer Support/ Technical Service:800-372-3331 · OEM Support: 866-915-5886

08/02/13