


PHILIPS ADVANCE

Metal
Halide
Lamp Ballast


Catalog Number 71A67J2
For 1500W M48
60 Hz CWA
Status: Active

DIMENSIONS AND DATA



INPUT VOLTS	220				
CIRCUIT TYPE	CWA				
POWER FACTOR (min)	90%				
REGULATION					
Line Volts	±10%				
Lamp Watts	±10%				
LINE CURRENT (Amps)					
Operating.....	7.40				
Open Circuit.....	2.35				
Starting.....	7.30				
UL TEMPERATURE RATINGS					
Insulation Class	N(200°C)				
Coil Temperature Code	1029				
MIN. AMBIENT STARTING TEMP.	-20°F or -30°C				
NOM. OPEN CIRCUIT VOLTAGE	440				
INPUT VOLTAGE AT LAMP DROPOUT.....	150				
INPUT WATTS	1610				
RECOMMENDED FUSE (Amps).....	25				
CORE and COIL					
Dimension (A)	4.00				
Dimension (B)	6.00				
Weight (lbs.)	29				
Lead Lengths	18"				
CAPACITOR REQUIREMENT					
Microfarads	32.0				
Volts (min.)	525				
Fault Current Withstand (amps)					
60 Hz TEST PROCEDURES (Refer to Advance Test Procedure for HID Ballasts - Form 1270)					
High Potential Test (Volts)					
1 minute	2000				
2 seconds	2500				
Open Circuit Voltage Test (Volts)	405-495				
Short-Circuit Current Test (Amps)					
Secondary Current	7.55-9.75				
Input Current.....	5.30-9.60	-	-	-	-

Capacitor: MD3202-100



Capacitance: 32
Dia/Oval Dim: 2.00
Height: 3.75
Temp Rating: 90°C

Wiring Diagram:




Fig. A

Ordering Information

Order Suffix	Description
500.	Ballast with Oil Filled Capacitor

Ignitor: NA

This ballast does not
require the use of an ignitor.

Data is based upon tests performed by Philips Lighting Electronic N.A. in a controlled environment and representative of relative performance. Actual performance can vary depending on operating conditions. Specifications are subject to change without notice.

Philips Lighting Electronic N.A.

10275 West Higgins Road · Rosemont, IL 60018 · Tel:800-322-2086 Fax:888-432-1882
Customer Support/ Technical Service:800-372-3331 · OEM Support: 866-915-5886

08/30/13