

As easy as 1, 2, 3

Mark 10 Powerline

For companies looking to make their fixed-output linear T8, 4-pin CFL, and T5/HO fluorescent systems more cost effective and sustainable, Mark 10 Powerline ballasts provide an easy solution without the need for additional control leads. Simply, (1) replace the ballast, (2) replace the switch, (3) dim the lights, that is all it takes. It's that easy to bring the convenience and flexibility of fluorescent dimming to conference rooms, private offices, auditoriums, architectural cove lighting – anywhere dimming is required.

Avantages

- Compatible with controls from numerous manufacturers without using separate control leads - Powerline dimming interface
- Ideal for frequent switching applications such as occupancy sensors and daylight harvesting - Programmed start operation

Fonctions

- Available in linear fluorescent and 4-pin compact fluorescent models
- Full range continuous dimming (100% light output down to 5% - T5HO to 1%)

Application

- Conference rooms, private offices, auditoriums, architectural cove, auditoriums, educational facilities, hotels, restaurants, and department stores


Les données sont sujettes à changement

Mark 10 Powerline

Versions
























Schéma dimensionnel




Product	A1	A2	B1	C1
MARK 10 POWERLINE VEZ2S5435M	16,70 in	16,34 in	1,18 in	1,00 in
MARK 10 POWERLINE REZ15435M	16,70 in	16,34 in	1,18 in	1,00 in
MARK 10 POWERLINE IEZ2S24D35M	16,70 in	16,34 in	1,18 in	1,00 in
MARK 10 POWERLINE IEZ2S28D35M	16,7 in	1,18 in	1,0 in	
MARK 10 POWERLINE IEZ128D35M	16,7 in	1,18 in	1,0 in	
MARK 10 POWERLINE VEZ15435M	16,70 in	16,34 in	1,18 in	1,00 in
MARK 10 POWERLINE REZ2S5435M	16,70 in	16,34 in	1,18 in	1,00 in


Schéma dimensionnel




Product	A1	A2	B1	C1
MARK 10 POWERLINE REZ2TTS40SC35M	9,5 in	8,90 in	1,7 in	1,18 in
MARK 10 POWERLINE REZ2S32SC35I	9,5 in	8,90 in	1,7 in	1,18 in
MARK 10 POWERLINE REZ1TTS40SC35M	9,5 in	8,90 in	1,7 in	1,18 in
MARK 10 POWERLINE REZ132SC35M	9,5 in	8,90 in	1,7 in	1,18 in
MARK 10 POWERLINE VEZ132SC35M	9,5 in	8,90 in	1,7 in	1,18 in
MARK 10 POWERLINE VEZ3S32SC35M	9,5 in	8,90 in	1,7 in	1,18 in
MARK 10 POWERLINE VEZ2S32SC35M	9,5 in	8,90 in	1,7 in	1,18 in
MARK 10 POWERLINE REZ3S32SC35M	9,5 in	8,90 in	1,7 in	1,18 in
MARK 10 POWERLINE REZ2S32SC35M	9,5 in	8,90 in	1,7 in	1,18 in



Product	A1	A2	A3	B1	C1
MARK 10 POWERLINE VEZ1T42M2BS35M	4,55 in	4,20 in	2,00 in	3,00 in	1,29 in
MARK 10 POWERLINE REZ2T42M3BS35M	6,0 in	5,5 in	2,00 in	3,00 in	1,29 in
MARK 10 POWERLINE REZ2Q26M2BS35M	4,55 in	4,20 in	2,00 in	3,00 in	1,29 in
MARK 10 POWERLINE REZ1T42M2BS35M	4,55 in	4,20 in	2,00 in	3,00 in	1,29 in



Product	A1	A2	B1	C1
MARK 10 POWERLINE REZ2Q18M2LD35M	4,55 in	4,20 in	3,00 in	1,29 in
MARK 10 POWERLINE VEZ2Q26M2LD35M	4,55 in	4,20 in	3,00 in	1,29 in
MARK 10 POWERLINE REZ2Q26M2LD35M	4,55 in	4,20 in	3,00 in	1,29 in
MARK 10 POWERLINE VEZ1T42M2LD35M	4,55 in	4,20 in	3,00 in	1,29 in
MARK 10 POWERLINE REZ1T42M2LD35M	4,55 in	4,20 in	3,00 in	1,29 in



Product	A1	A2	B1	C1
MARK 10 POWERLINE REZ2T42M3LD35M	6,0 in	5,5 in	3,00 in	1,29 in

Fonctionnement et électricité

Distorsion harmonique totale États-Unis	10 %

Mark 10 Powerline

Fonctionnement et électricité

Order Code	Full Product Name	Fréquence d'entrée	Tension d'entrée
176230	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F54T5/H0 120V	60 Hz	120 V
176248	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F54T5/HO 120V	60 Hz	120 V
176669	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F54T5/HO 277V	60 Hz	277 V
176677	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F54T5/HO 277V	60 Hz	277 V
176685	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 120V	60 Hz	120 V
176842	MARK 10 POWERLINE ELE DIM BALLAST (2) 26W CFL (4-PIN) 120V	60 Hz	120 V
116426	MARK 10 POWERLINE ELE DIM BALLAST (2) 18W CFL (4-PIN) 120V	60 Hz	120 V
176693	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 277V	60 Hz	277 V
182543	MARK 10 POWERLINE ELE DIM BALLAST (2) 26W CFL (4-PIN) 277V	60 Hz	277 V
176701	MARK 10 POWERLINE ELE DIM BALLAST (2) 42W CFL (4-PIN) 120V	60 Hz	120 V
183053	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F32T8 120V	60 Hz	120 V
182204	MARK 10 POWERLINE ELE DIMMING BALLAST (3) F32T8 120V	60 Hz	120 V
191056	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F32T8 120V	60 Hz	120 V

Order Code	Full Product Name	Fréquence d'entrée	Tension d'entrée
116400	MARK 10 POWERLINE ELE DIM BALLAST (1) 40W CFL (4-PIN) 120V	60 Hz	120 V
116442	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F32T8 120V	60 Hz	120 V
119883	MARK 10 POWERLINE ELE DIM BALLAST (2) 40W CFL (4-PIN) 120V	60 Hz	120 V
182162	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 120V	60 Hz	120 V
182188	MARK 10 POWERLINE ELE DIM BALLAST (2) 26W CFL (4-PIN) 120V	60 Hz	120 V
182196	MARK 10 POWERLINE ELE DIM BALLAST (2) 42W CFL (4-PIN) 120V	60 Hz	120 V
183467	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F32T8 277V	60 Hz	277 V
183616	MARK 10 POWERLINE ELE DIMMING BALLAST (3) F32T8 277V	60 Hz	277 V
183707	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F32T8 277V	60 Hz	277 V
500751	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F28T5 120-277V	50 à 60 Hz	120 to 277 V
500777	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F28T5 120-277V	50 à 60 Hz	120 to 277 V
121186	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F24T5HO 120-277V	50 à 60 Hz	120 to 277 V
118232	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 277V	60 Hz	277 V

Renseignements généraux

Order Code	Full Product Name	Nombre de lampes	Type de lampe
176230	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F54T5/H0 120V	1 piece/unit	F54T5/HO
176248	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F54T5/HO 120V	2 piece/unit	F54T5/HO
176669	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F54T5/HO 277V	1 piece/unit	F54T5/HO
176677	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F54T5/HO 277V	2 piece/unit	F54T5/HO
176685	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 120V	1 piece/unit	CFTR42W/ GX24Q
176842	MARK 10 POWERLINE ELE DIM BALLAST (2) 26W CFL (4-PIN) 120V	2 piece/unit	CFQ26W/G24Q
116426	MARK 10 POWERLINE ELE DIM BALLAST (2) 18W CFL (4-PIN) 120V	2 piece/unit	CFQ18W/G24Q
176693	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 277V	1 piece/unit	CFTR42W/ GX24Q
182543	MARK 10 POWERLINE ELE DIM BALLAST (2) 26W CFL (4-PIN) 277V	2 piece/unit	CFQ26W/G24Q

Order Code	Full Product Name	Nombre de lampes	Type de lampe
176701	MARK 10 POWERLINE ELE DIM BALLAST (2) 42W CFL (4-PIN) 120V	2 piece/unit	CFTR42W/ GX24Q
183053	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F32T8 120V	2 piece/unit	F32T8
182204	MARK 10 POWERLINE ELE DIMMING BALLAST (3) F32T8 120V	3 piece/unit	F32T8
191056	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F32T8 120V	1 piece/unit	F32T8
116400	MARK 10 POWERLINE ELE DIM BALLAST (1) 40W CFL (4-PIN) 120V	1 piece/unit	FT40W/2G11
116442	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F32T8 120V	2 piece/unit	F32T8
119883	MARK 10 POWERLINE ELE DIM BALLAST (2) 40W CFL (4-PIN) 120V	2 piece/unit	FT40W/2G11
182162	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 120V	1 piece/unit	CFTR42W/ GX24Q
182188	MARK 10 POWERLINE ELE DIM BALLAST (2) 26W CFL (4-PIN) 120V	2 piece/unit	CFQ26W/G24Q

Mark 10 Powerline

Order Code	Full Product Name	Nombre de lampes	Type de lampe
182196	MARK 10 POWERLINE ELE DIM BALLAST (2) 42W CFL (4-PIN) 120V	2 piece/unit	CFTR42W/ GX24Q
183467	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F32T8 277V	2 piece/unit	F32T8
183616	MARK 10 POWERLINE ELE DIMMING BALLAST (3) F32T8 277V	3 piece/unit	F32T8
183707	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F32T8 277V	1 piece/unit	F32T8

Order Code	Full Product Name	Nombre de lampes	Type de lampe
500751	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F28T5 120-277V	1 piece/unit	F28T5
500777	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F28T5 120-277V	2 piece/unit	F28T5
121186	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F24T5HO 120-277V	2 piece/unit	F24T5/HO
118232	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 277V	1 piece/unit	CFTR42W/ GX24Q

Mécanique et boîtier

Order Code	Full Product Name	Boîtier
176230	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F54T5/H0 120V	D
176248	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F54T5/HO 120V	D
176669	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F54T5/HO 277V	D
176677	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F54T5/HO 277V	D
176685	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 120V	M2
176842	MARK 10 POWERLINE ELE DIM BALLAST (2) 26W CFL (4-PIN) 120V	M2
116426	MARK 10 POWERLINE ELE DIM BALLAST (2) 18W CFL (4-PIN) 120V	M2
176693	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 277V	M2
182543	MARK 10 POWERLINE ELE DIM BALLAST (2) 26W CFL (4-PIN) 277V	M2
176701	MARK 10 POWERLINE ELE DIM BALLAST (2) 42W CFL (4-PIN) 120V	M3
183053	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F32T8 120V	SC
182204	MARK 10 POWERLINE ELE DIMMING BALLAST (3) F32T8 120V	SC
191056	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F32T8 120V	SC
116400	MARK 10 POWERLINE ELE DIM BALLAST (1) 40W CFL (4-PIN) 120V	SC

Order Code	Full Product Name	Boîtier
116442	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F32T8 120V	SC
119883	MARK 10 POWERLINE ELE DIM BALLAST (2) 40W CFL (4-PIN) 120V	SC
182162	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 120V	M2
182188	MARK 10 POWERLINE ELE DIM BALLAST (2) 26W CFL (4-PIN) 120V	M2
182196	MARK 10 POWERLINE ELE DIM BALLAST (2) 42W CFL (4-PIN) 120V	M3
183467	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F32T8 277V	SC
183616	MARK 10 POWERLINE ELE DIMMING BALLAST (3) F32T8 277V	SC
183707	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F32T8 277V	SC
500751	MARK 10 POWERLINE ELE DIMMING BALLAST (1) F28T5 120-277V	D
500777	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F28T5 120-277V	D
121186	MARK 10 POWERLINE ELE DIMMING BALLAST (2) F24T5HO 120-277V	D
118232	MARK 10 POWERLINE ELE DIM BALLAST (1) 42W CFL (4-PIN) 277V	M2

© 2018 Signify Holding Tous droits réservés. Signify ne fait aucune déclaration ni ne donne aucune garantie quant à l'exactitude et à l'exhaustivité des informations fournies dans les présentes et ne serait être tenu responsable de toute mesure prise sur leur fondement. Les informations présentées dans ce document ne constituent pas une offre commerciale et ne font partie d'aucun devis ni contrat, à moins qu'il n'en soit convenu autrement avec Signify. Toutes les marques déposées appartiennent à Signify Holding et à leurs propriétaires respectifs.