

# BTA EM ballasts for TL Fluorescent lamps

## BTA 36W 220V/60Hz C SC

This efficient, reliable, long-life electromagnetic ballast for TL-D fluorescent lamps features a balanced combination of essential characteristics, thus allowing a wide variety of standard applications.


### Product data

Operating and Electrical	
Input Voltage	220 V
Line Frequency	60 Hz
Input Frequency	60 Hz
Wiring	
Connector Type	Screw
Mechanical and Housing	
Housing	L 155x39x28
Approval and Application	
Energy Efficiency Index	C
Approval Marks	CE marking

Product Data	
Order product name	BTA 36W 220V/60Hz C SC
Full product name	BTA 36W 220V/60Hz C SC
Full product code	871016303544430
Order code	913710118443
Material Nr. (12NC)	913710118443
Numerator - Quantity Per Pack	1
EAN/UPC - Product/Case	8710163149950
Numerator - Packs per outer box	32
EAN/UPC - Case	8710163065151

## BTA EM ballasts for TL Fluorescent lamps

### Dimensional drawing



Product	D1	C1	C3	A1	A2	A3	A4	B1	B2
BTA 36W	4.0	28.0	1.2	155.0	140.0	48.0	48.0	39.0	20.0
220V/60Hz	mm	mm	mm	mm	mm	mm	mm	mm	mm
C SC									

