



## EB-Certalume for TL5 lamps

## EB-C 128 TL5 220-240V 50/60Hz

Affordable, reliable, high frequency electronic ballast for TL5 fluorescent lamps, ideal alternative for electromagnetic (EM) ballasts


## **Product data**

Operating and Electrical				
Input Voltage	220 to 240 V			
Line Frequency	50 to 60 Hz			
Input Frequency	50 to 60 Hz			
Earth Leakage Current (Max)	0.7 mA			
Wiring				
Connector Type Input Terminals	250 manual connector [Suitable for manual wiring			
	and easy release button]			
Color Input Terminals	Orange			
Color Output Terminals	Grey			
Connector Type Output Terminals	250 manual connector [Suitable for manual wiring			
	and easy release button]			
Temperature				
T-Case Lifetime (Nom)	75 ℃			
Mechanical and Housing				
Housing	L 275x20x21			

A second and A sould and the				
Approval and Application				
Ingress protection code	IP20 [Finger-protected]			
Energy Efficiency Index	A2			
Approval Marks	CCC certificate CB Certificate			
Product Data				
Order product name	EB-C 128 TL5 220-240V 50/60Hz			
Full product name	EB-C 128 TL5 220-240V 50/60Hz			
Full product code	872790088656600			
Order code	913713196414			
Material Nr. (12NC)	913713196414			
Numerator - Quantity Per Pack	1			
EAN/UPC - Product/Case	8711500998927			
Numerator - Packs per outer box	50			
EAN/UPC - Case	8727900886566			

## EB-Certalume for TL5 lamps

Dimensional drawing



Product	D1	C1	A1	A2	B1
EB-C 128 TL5 220-240V 50/60Hz	4.2 mm	21.0 mm	275.0 mm	265.0 mm	19.8 mm



© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.

www.lighting.philips.com 2023, April 17 - data subject to change