



Product Description

Safety & Comfort Starters

Range of premium quality electronic starters for igniting fluorescent lamps operating on conventional electromagnetic ballast.

Benefits

- S2E – S10E
- Lower cost of lighting ownership: – Lamps last much longer thanks to a totally smooth, flicker-free and fast starting. / – Electronic starters turn off lamps at end of life, which avoids irritation (no flickering), useless electricity consumption and fire risk. / – Longer starter service life compared to conventional starters
- Contribution to a green environment (no lead and no radioactivity)
- Flame-retardant components & UV resistant canister lead to additional safety and a secure ignition
- Easy recognition & installation and replacement friendly
- SiS10
- Lower cost of lighting ownership: – SiS 10 starter turns off lamps at end of life, which avoids irritation (no flickering), useless electricity consumption and fire risk. / – 4 times longer service life compared to conventional starters
- System is immediately ready for use again by simply pressing the red button following an interruption
- Contribution to a green environment (no lead and no radioactivity)
- Flame-retardant components & UV resistant canister lead to additional safety and a secure ignition

Safety & Comfort Starters

Features

- S2E – S10E
- Instant flicker-free ignition (nom. 2.3 sec)
- Full thermal safety monitor which cuts off defective or end-of-life lamps
- Cut-off circuit to protect the starter and overheating of the control gear
- Premium reliability with 100.000 safe switches
- Radioactive-free (patented) and lead-free (RoHS-compliant)
- 2-pin igniter in plastic (flame-retardant polycarbonate) canister
- Narrowed top & installation notch
- SiS10
- Reliable automatic disconnection of defective or end-of-life fluorescent lamps
- Cut-off circuit to protect the starter and overheating of the control gear
- Button with 3x restart function
- Premium reliability with 10.000 safe switches
- Radioactive-free (patented) and lead-free (RoHS-compliant)
- 2-pin igniter in plastic (flame-retardant polycarbonate) canister with radio-interference suppression capacitor

Application

- Starters are used in conventional electromagnetic fluorescent lamp systems using TL-D (T8), TL (T12), TL mini, PL-S and PL-L lamps.
- S2-E starters are suitable for:
 - 110/130V, 18-22W single applications
 - 220/240V, 18-22W series applications
- S10-E starters are suitable for:
 - 220/240V, 18-75W single applications
- SiS 10 starters are suitable for:
 - 220/240V, 30-65W single applications
- As for the SiS 10 starter, always press the red button after replacing a lamp so that the system is operational again.


Versions



LPPR STARTER S2E BL PHL

Safety & Comfort Starters

Dimensional drawing



Product	C (max)	E (max)
S10E 18-75W SIN 220-240V BL/20X25CT	40.3 mm	21.5 mm

Product details



S10E, 18-75W, BL

