



Reliable performance

Core & Coil (71A) MH ~GT~ 450W

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Benefits

- Vacuum-pressure impregnation is used to re-enforce the electrical insulation of the ballast, preclude moisture, inhibit noise, and dissipate heat
- Pre-insulated voltage leads reduce the risk of shock and shrink installation time

Features


- Vacuum-pressure impregnated with a silica-filled polyester varnish
- All core and coil ballasts below 600W utilize a UL Class H (180°C) insulation system
- C and C ballasts 600W and higher utilize a UL Class N (200°C) insulation system
- Pre-insulated voltage leads
- Ballast kits supplied with pre-wired ignitor

Application


- High bay retail, manufacturing, gymnasiums, warehouses, parking structures, outdoor

Core & Coil (71A) MH ~GT~ 450W

Versions



Dimensional drawing



Product	C1	C2	A1	A2	A3	B1	B2
CORE & COIL HID 71A6772001	6.7 in	4.7 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A6542001	4.5 in	2.6 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A6572001	5 in	3.05 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID MH BAL 1000W M47 QUAD C&C	4.5 in	2.57 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in

Operating and Electrical

Input Frequency 60 Hz

General Information

Number Of Lamps 1 piece/unit

Operating and Electrical

Order Code	Full Product Name	Input Voltage
		120/208/240/277 V
		120/208/240/277 V

Order Code	Full Product Name	Input Voltage
		480/120T V
		120/208/240/277 V

General Information

Order Code	Full Product Name	Capacitor Value	Lamp Type
		24 MFD	1000W MH
		24 MFD	1000W MH

Order Code	Full Product Name	Capacitor Value	Lamp Type
		24 MFD	1000W MH
		32 MFD	1500W MH

Core & Coil (71A) MH ~GT~ 450W

