



Core & Coil (71A) HPS ~LT~ 200W

CORE & COIL HID HPS BAL 150W S55 QUAD KIT

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

S55
150W HPS
1 piece/unit
HX-HPF
Magnetic HID
71A8192
3 X 4 (2 LW)
Yes
LI551-H4
105°C
14 MFD
7C140M30RA
280V
105°C
1.65 in
2.75 in
No
120/208/240/277 V


Input Frequency	60 Hz											
Inp. Current (Open Circuit)	2.8/1.6/1.4/1.25 A											
Input Current (Starting)	2/1.15/1/0.85 A						2/1.15/1/0.85 A					
Input Current (Short Circuit)	1.15-1.75/0.65-1/0.55-0.85/0.5-0.75 A											
Secondary Short Circuit Current	3.95-4.85 A											
Constant Wattage Deviation	Within Trapezoid											
Ballast Factor (Nom)	1											
Power Factor (Nom)	0.90											
Nominal Open Circuit Voltage	120 V											
Input Current (Operating) (Nom)	1.65/0.95/0.83/0.72 A A											
Input Power (Nom)	190 W											
Rated Lamp Watts	150 W											
Wiring												
Wire Striplength	0.5 mm											
Wire Length by Color	12"											
Wire Type	Stranded											
Remote Wiring Configuration Allowed	Yes											
Max Ballast-Lamp Distance Remote	2'											
Wiring												

Core & Coil (71A) HPS ~LT~ 200W

Recommended Fuse Value	10/5/5/4 A				
Approval and Application					
Open Circuit Voltage Test (Volts)	110-130 V				
Approbation Marks	ULR CSA certificate RoHS Compliant				
Temperature Marking	E/E/E/E				
UL Recognized	Yes				
Hipot Test (1 Minute)	2000 V				
Hipot Test (2 Seconds)	2500 V				
UL Insulation Class	H(180°C)				
UL Temperature Code	1029E				

CORE & COIL HID HPS BAL 150W S55 QUAD KIT
781087052594
71A8192001DC
1
1
913700502909
3.888 kg

Dimensional drawing



HPS BAL 150W S55 QUAD KIT

Product	C1	C2	A1	A2	B1	B2
CORE & COIL HID HPS BAL 150W S55	4.2 in	2.5 in	3.9 in	3.5 in	2.8 in	2.4 in
QUAD KIT						



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2019, March 22 - data subject to change