



Standard

STANDARD MAG BALLAST (1) 9W COMPACT(2-PIN) 120V

Available for many fluorescent lamp types sold today, including Preheat, Rapid Start, 2-pin CFL, Slimline, High Output, Very High Output and Circline. Magnetic ballasts can be used in any application where these lamps are used.

Product data

General Information	
Lamp Type	CFQ9W/G23
Number of Lamps	1 piece/unit
Lamp Footage	-
Ballast Type	Magnetic Fluorescent
Base Model	H1B9TPW
Suitable For Outdoor Use	Yes
Automatic Restart	Yes
Operating and Electrical	
Input Voltage	120 V
Input Frequency	60 Hz
Total Harmonic Distortion USA	20 %
Ignition Method	Preheat
Crestfactor (Nom)	1.5
Ignition Time (Nom)	1s
Input Current (Open Circuit)	0.13
Input Current (Starting)	0.2
Ballast Factor (Nom)	0.92
Power Factor (Nom)	0.91
Input Current (Nom)	0.1 A
Input Power (Nom)	11 W


Rated Lamp Power	9 W		
Wiring			
Wire Striplength	0.50/0.375 mm		
Lamp Connection	Series		
Wire Length by Color	See data sheet		
Wire Gauge (Nom)	18AWG mm		
Wire Type	Solid		
Remote Wiring Configuration Allowed	Yes		
Tandem Wiring Configuration Allowed	No		
Through Wiring Configuration Allowed	No		
Max Ballast-Lamp Distance Remote Wiring	30'		
Max Ballast-Lamp Distance Tandem Wiring	-		
Max Ballast-Lamp Distance Through Wiring -			
Mechanical and Housing			
Housing Material	Metal		
Housing	R1		
Housing Dimensions	4.25" x 2.0" x 1.44"		
Approval and Application			
EMC Immunity Standard	FCC Non-Consumer		

Standard

Approval Marks	CSA certificate UL certificate RoHS			
	Compliant			
Hum And Noise Level	A			
UL Recognized	No			
Product Data				
Order product name	STANDARD MAG BALLAST (1) 9W			
	COMPACT(2-PIN) 120V			

EAN/UPC - Product	781087068281
Order code	913700506409
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	36
Material Nr. (12NC)	913700506409
Net Weight (Piece)	314.000 g

Dimensional drawing



Product	A1	A2	B1	C1
STANDARD MAG BALLAST (1) 9W COMPACT(2-	4.25 in	3.56 in	2 in	1.44 in
PIN) 120V				

MAG BALLAST (1) 9W COMPACT(2-PIN) 120V



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2019, March 22 - data subject to change