



# **PrimaVision Power for CDM**

# HID-PV C 100 /S CDM 220-240V 50/60Hz G5

PrimaVision Power gear is designed for optimal performance of 100 and 150 W CDM lamps – ideal where high-intensity light is key.

#### **Product data**


Operating and Electrical	
Input Voltage	220 to 240 V
Line Frequency	50 to 60 Hz
Input Frequency	50 to 60 Hz
Earth Leakage Current (Max)	0.25 mA
Inrush Current Width	0.40 ms
Inrush Current Peak (Max)	40 A
Number of Products on MCB (16A Type B)	17
(Nom)	
Wiring	
Cable Length From Device to Lamp	2 m
Connector Type	Insert
Temperature	
Ambient temperature range	-20 °C to 50 °C
T-Case Lifetime (Nom)	75 °C
T-Case Maximum (Max)	75 °C
Mechanical and Housing	
Housing	/S

IP20 [Finger-protected]		
ertificate		
M 220-240V 50/60Hz		
M 220-240V 50/60Hz		

Datasheet, 2023, August 28 data subject to change

## **PrimaVision Power for CDM**

### Dimensional drawing





Product	A1	A2	B1	B2	C1	D1
HID-PV C 100 /S CDM	135.0 mm	123.5 mm	75.0 mm	63.5 mm	32.0 mm	4.5 mm
220-240V 50/60Hz G5						



© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.