

BTA EM ballasts for TL Fluorescent lamps

BTA 36W 220V/60Hz C SC

This efficient, reliable, long-life electromagnetic ballast for TL-D fluorescent lamps features a balanced combination of essential characteristics, thus allowing a wide variety of standard applications.


Product data

Operating and Electrical	
Input Voltage	220 V
Line Frequency	60 Hz
Input Frequency	60 Hz
Wiring	
Connector Type	Screw
Mechanical and Housing	
Housing	L 155x39x28
Approval and Application	
Energy Efficiency Index	C
Approval Marks	CE marking

Product Data	
Full product code	871016303544430
Order product name	BTA 36W 220V/60Hz C SC
Order code	913710118443
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	32
Material Nr. (12NC)	913710118443
Full product name	BTA 36W 220V/60Hz C SC
EAN/UPC - Case	8710163065151
EAN/UPC - Product/Case	8710163149950

BTA EM ballasts for TL Fluorescent lamps

Dimensional drawing



Product	D1	C1	C3	A1	A2	A3	A4	B1	B2
BTA 36W	4.0	28.0	1.2	155.0	140.0	48.0	48.0	39.0	20.0
220V/60Hz	mm	mm	mm	mm	mm	mm	mm	mm	mm
C SC									

