



Standard

STANDARD MAG BALLAST (1) 26W COMPACT(2-PIN) 277V

Available for many fluorescent lamp types sold today, including Preheat, Rapid Start, 2-pin CFL, Slimline, High Output, Very High Output and Circline. Magnetic ballasts can be used in any application where these lamps are used.

Product data

General Information			
Lamp Type	CFQ26W/G24D		
Number of Lamps	1 piece/unit		
Lamp Footage	-		
Ballast Type	Magnetic Fluorescent		
Base Model	VH1Q26TPW		
Suitable For Outdoor Use	Yes		
Automatic Restart	Yes		
Operating and Electrical			
Input Voltage	277 V		
Input Frequency	60 Hz		
Total Harmonic Distortion USA	20 %		
Ignition Method	Preheat		
Crestfactor (Nom)	1.5		
Ignition Time (Nom)	1s		
Input Current (Open Circuit)	0.24		
Input Current (Starting)	0.38		
Ballast Factor (Nom)	0.9		
Power Factor (Nom)	0.98		
Input Current (Nom)	0.11 A		
Input Power (Nom)	31 W		


Rated Lamp Power	26 W
Wiring	
Wire Striplength	0.50/0.375 mm
Lamp Connection	Series
Wire Length by Color	See data sheet
Wire Gauge (Nom)	18AWG mm
Wire Type	Solid
Remote Wiring Configuration Allowed	Yes
Tandem Wiring Configuration Allowed	No
Through Wiring Configuration Allowed	No
Max Ballast-Lamp Distance Remote Wiring	30'
Max Ballast-Lamp Distance Tandem Wiring	-
Max Ballast-Lamp Distance Through Wiring	-
Mechanical and Housing	
Housing Material	Metal
Housing	R2
Housing Dimensions	4.75" x 2.22" x 1.63"
Approval and Application	
EMC Immunity Standard	FCC Non-Consumer

Standard

Approval Marks	CSA certificate UL certificate RoHS			
	Compliant			
Hum And Noise Level	A			
UL Recognized	No			
Product Data				
Order product name	STANDARD MAG BALLAST (1) 26W			
	COMPACT(2-PIN) 277V			

EAN/UPC - Product	781087068236
Order code	913710315502
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	24
Material Nr. (12NC)	913710315502
Net Weight (Piece)	0.667 kg

Dimensional drawing



Product	A1	A2	B1	C1
STANDARD MAG BALLAST (1) 26W	4.75 in	4.38 in	2.22 in	1.63 in
COMPACT(2-PIN) 277V				

MAG BALLAST (1) 26W COMPACT(2-PIN) 277V



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2019, March 22 - data subject to change