



Core & Coil (71A) MH ~LT~ 175W

CORE & COIL HID MH BAL 70W M98/143 127/220V C&C

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

| General Information | | | | |
|------------------------------------|----------------|--|--|--|
| ANSI Code | M98-M143 | | | |
| Lamp Type | 70W MH | | | |
| Number of Lamps | 1 piece/unit | | | |
| Circuit Type | HX-HPF | | | |
| Ballast Type | Magnetic HID | | | |
| Base Model | 71A52H2 | | | |
| Core Size | 3 X 4 (2 coil) | | | |
| Suitable For Outdoor Use | Yes | | | |
| Ignitor Catalog Number | LI534-H5 | | | |
| Ignitor Temperature Rating | 105°C | | | |
| Capacitor Value | 8 MFD | | | |
| Capacitor Catalog Number | 7C080L30RA | | | |
| Capacitor Requirements | 280V | | | |
| Capacitor Temperature Rating | 105°C | | | |
| Capacitor Diameter/Oval Dimensions | 1.25 in | | | |
| Capacitor Height | 2.75 in | | | |
| Automatic Restart | No | | | |
| | | | | |

| Operating and Electrical | | | | | |
|-------------------------------------|--------------------|--|--|--|--|
| Input Voltage | 127/220 V | | | | |
| Input Frequency | 60 Hz | | | | |
| Inp. Current (Open Circuit) | 1.9/0.85 A | | | | |
| Input Current (Starting) | 0.5/0.35 A | | | | |
| Input Current (Short Circuit) | 0.55-0.8/0.3-0.5 A | | | | |
| Secondary Short Circuit Current | 0.95-1.25 A | | | | |
| Constant Wattage Deviation | 10% | | | | |
| Ballast Factor (Nom) | 1 | | | | |
| Power Factor (Nom) | 0.90 | | | | |
| Nominal Open Circuit Voltage | 255 V | | | | |
| Input Current (Operating) (Nom) | 0.82/0.48 A A | | | | |
| Input Power (Nom) | 94 W | | | | |
| Rated Lamp Watts | 70 W | | | | |
| | | | | | |
| Wiring | | | | | |
| Wire Striplength | 0.5 mm | | | | |
| Wire Length by Color | 12" | | | | |
| Wire Type | Stranded | | | | |
| Remote Wiring Configuration Allowed | Yes | | | | |


Datasheet, 2019, March 8 data subject to change

Core & Coil (71A) MH ~LT~ 175W

| Max Ballast-Lamp Distance Remote Wiring 15' | | | | | |
|---|------------------------------------|--|--|--|--|
| Recommended Fuse Value | 4/2 A | | | | |
| Approval and Application | | | | | |
| Open Circuit Voltage Test (Volts) | 230-280 V | | | | |
| Approbation Marks | NOM certificate RoHS Compliant CSA | | | | |
| | certificate | | | | |
| Temperature Marking | A/A | | | | |
| UL Recognized | Yes | | | | |
| Hipot Test (1 Minute) | 2000 V | | | | |
| Hipot Test (2 Seconds) | 2500 V | | | | |
| UL Insulation Class | H(180°C) | | | | |
| UL Temperature Code | 1029A | | | | |

| Product Data | | | | |
|---------------------------------|------------------------------------|--|--|--|
| Order product name | CORE & COIL HID MH BAL 70W M98/143 | | | |
| | 127/220V C&C | | | |
| EAN/UPC - Product | 781087034736 | | | |
| Order code | 71A52H2500DML | | | |
| Numerator - Quantity Per Pack | 1 | | | |
| Numerator - Packs per outer box | 2 | | | |
| Material Nr. (12NC) | 913710486802 | | | |
| Net Weight (Piece) | 2.482 kg | | | |

Dimensional drawing



MH BAL 70W M98/143 127/220V C&C

| Product | C1 | C2 | A1 | A2 | B1 | B2 |
|-------------------------------|---------|---------|--------|--------|--------|--------|
| CORE & COIL HID 71A52H2500DML | 2.75 in | 1.45 in | 3.9 in | 3.5 in | 2.8 in | 2.4 in |

