



Optanium Step Dim

OPTANIUM ELE BALLAST (2) F28T5 120-277V

Philips Advance Optanium ballasts with step-dim capability for T5 and T8 fluorescent lamps represent an affordable, energy-efficient, and versatile lighting solution designed to meet energy codes such as California's Title 24 and ASHRAE 90.1-2010 that require end users to reduce lighting power consumption by 50%. Operating from any line voltage switching device, the ballast's programmed-start circuitry provides extended lamp life in frequent switching applications like those associated with the use of occupancy sensors or motion detectors making this product the sustainable choice for many commercial applications.

Product data

| General Information | | | | |
|---------------------------------|------------------------|--|--|--|
| Lamp Type | F28T5 | | | |
| Number of Lamps | 1/2 piece/unit | | | |
| Ballast Type | Electronic Fluorescent | | | |
| Base Model | IOP2S28115SCSD | | | |
| Suitable For Outdoor Use | Yes | | | |
| Automatic Restart | Yes | | | |
| | | | | |
| Operating and Electrical | | | | |
| Input Voltage | 120 to 277 V | | | |
| Input Frequency | 50 to 60 Hz | | | |
| Max THD | 10 % | | | |
| Starting Method | Programmed Start | | | |
| Lamp Current Crest Factor (Nom) | 1.6 | | | |
| Ignition Time (Nom) | 1.5 s | | | |
| Ballast Factor (Nom) | 1.15 | | | |
| Power Factor (Nom) | 0.98 | | | |
| Input Current (Operating) (Max) | 0.60 A | | | |
| Input Current (Operating) (Min) | 0.26 A | | | |
| | | | | |

| Input Power (Nom) | 72-71 W | | |
|---|----------------|--|--|
| Rated Lamp Watts | 28 W | | |
| | | | |
| Wiring | | | |
| Color Input Terminals | No terminals | | |
| Color Output Terminals | No terminals | | |
| Wire Striplength | 0.50/0.375 mm | | |
| Lamp Connection | Series | | |
| Wire Length by Color | See data sheet | | |
| Wire Gauge (Nom) | 18AWG mm | | |
| Wire Type | Solid | | |
| Remote Wiring Configuration Allowed | Yes | | |
| Tandem Wiring Configuration Allowed | Yes | | |
| Through Wiring Configuration Allowed | Yes | | |
| Max Ballast-Lamp Distance Remote Wiring | 7' | | |
| Max Ballast-Lamp Distance Tandem Wiring | Any = 7' | | |
| Max Ballast-Lamp Distance Through Wiring Any = 7' | | | |
| Connector Type | No connector | | |
| | | | |


Datasheet, 2019, March 22 data subject to change

Optanium Step Dim

| T | | | | | |
|--------------------------|--|--|--|--|--|
| Temperature | | | | | |
| T-Case Maximum (Nom) | 70 °C | | | | |
| | | | | | |
| Mechanical and Housing | | | | | |
| Housing Material | Metal | | | | |
| Housing | SC | | | | |
| Housing Dimensions | 9.5" × 1.7" × 1.18" | | | | |
| | | | | | |
| Approval and Application | | | | | |
| EMC Immunity Standard | FCC Non-Consumer | | | | |
| Approbation Marks | CSA certificate UL certificate CEC Listing | | | | |
| | RoHS Compliant | | | | |
| Sound Rating | A | | | | |

| UL Recognized | No |
|---------------------------------|--------------------------------|
| | |
| Product Data | |
| Order product name | OPTANIUM ELE BALLAST (2) F28T5 |
| | 120-277V |
| EAN/UPC - Product | 781087057643 |
| Order code | IOP2S28115SCSD35M |
| Numerator - Quantity Per Pack | 1 |
| Numerator - Packs per outer box | 20 |
| Material Nr. (12NC) | 913710815002 |
| Net Weight (Piece) | 404.000 g |

Dimensional drawing



ELE BALLAST (2) F28T5 120-277V

| Product | A1 | A2 | B1 | C1 |
|---|--------|---------|--------|---------|
| OPTANIUM ELE BALLAST (2) F28T5 120-277V | 9.5 in | 8.90 in | 1.7 in | 1.18 in |



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.