

Digital ignitors for maximum reliability

Electronic series ignitor for HID lamp circuits

HID ignitors for series systems

Benefits

- Easy installation and wiring
- Can operate with both semi-parallel and series ballasts
- Digital ignitors ensure maximum reliability


Features

- Ignitors equipped with screw terminal blocks as standard
- Series ignitor will only work in series circuits

Application

- Outdoor lighting (most popular application: roads and tunnels)

Dimensional drawing



Product	C1	A1	A2	B1	D1
SU 50	50 mm	90 mm	69 mm	55 mm	4.3 mm
SU 52	50 mm	90 mm	69 mm	55 mm	4.3 mm

Electronic series ignitor for HID lamp circuits

Operating and Electrical	
Input Frequency	50 to 60 Hz
Mechanical and Housing	
Housing	PC UL94V-2

Operating and Electrical

Order Code	Full Product Name	Input Voltage
913710011213	SU 50	220 to 240 V

Order Code	Full Product Name	Input Voltage
913710011313	SU 52	380-420 V

