

# Performer Maxos LED – iluminat liniar eficient şi precis

## Maxos LED Performer

Clienții doresc să diminueze consumul de energie şi cheltuielile în comparație cu ceea ce cunosc în materie de iluminat convențional. În acelaşi timp, sunt necesare condiții de iluminat excelente: în medii industriale, pentru a garanta siguranța şi productivitatea, iar în magazine, pentru a scoate în evidență marfa şi a atrage cumpărătorii. Maxos LED Performer este o soluție foarte flexibilă, care asigură un consum redus de energie şi o modelare excelentă a fasciculului luminos, la un nivel de investiție atrăgător.

**Beneficii**

- Amortizare foarte rapidă
- Sistem optic inovativ de ultimă generație pentru modelare exactă a fasciculului luminos
- Flexibilitate în ceea ce priveşte montarea retrofit pe instalații vechi, spoturi, modificări, accesorii

**Caracteristici**


- Consum redus de energie în comparație cu lămpile fluorescente
- Modelare excelentă a fasciculului luminos, pentru mai puțină lumină risipită şi distribuție exactă a luminii în plan orizontal şi vertical
- Motoare LED testate de la Philips (Fortimo)
- Posibilitate de montare pe instalații noi sau vechi, pe o şină Maxos
- Disponibil şi în variantă panou flexibil 4MX800 sau în variantă cu eficiență ridicată 4MX850


# Maxos LED Performer


## Cerere


- Supermarketuri
- Depozite
- Unități de producție

## Cote




## Detalii produs

**IPDP_4MX900i_0001-Detail photo**



**IPDP_4MX900i_0003-Detail photo**



## Detalii produs






IPDP_4MX900i_0011-Detail photo



# Maxos LED Performer

| Informaţii generale | |
|---|---|
| **Marcaj CE** | Da |
| **Balast inclus** | Da |
| **Marcaj ENEC** | Marcaj ENEC |
| **Marcaj de inflamabilitate** | - |
| **Test de incandescenţă** | Temperatură 650 °C, durată 30 s |
| **Sursă de lumină înlocuibilă** | Nu |
| **Număr de unităţi de echipament** | 1 unitate |
| **Cod familie de produse** | 4MX900 |
| **Date tehnice lumină** | |
| **Unghi de distribuţie sursă de lumină** | 120 ° |
| **Temperatură de culoare corelată (nom.)** | 4000 K |
| **Indice de redare a culorilor (IRC)** | ≥80 |
| **Număr de surse de lumină** | 1 |
| **Funcţionare şi sistem electric** | |
| **Tensiune de intrare** | De la 220 până la 240 V |
| **Frecvenţă linie** | 50 to 60 Hz |
| **Temperatură** | |
| **Interval temperatură ambientală** | De la -20 până la +40 ºC |
| **Aprobare şi aplicaţie** | |
| **Clasă de protecţie IEC** | Clasa de siguranţă I |
| **Cod de protecţie împotriva impactului mecanic** | IK02 |
| **Cod protecţie împotriva infiltrărilor** | IP40 |
| **Performanţă iniţială (conformitate IEC)** | |
| **Cromatică iniţială** | (0.38, 0.38) SDCM <3.5 |
| **Toleranţă flux luminos** | +/-10% |
| **Condiţii de utilizare** | |
| **Adecvat pentru comutare aleatorie** | Nu se aplică |

## Informaţii generale

| Order Code | Full Product Name | Cod familie lămpi |
|---|---|---|
| 66387399 | 4MX900 LED40S/840 PSD WB WH L1200 | LED40S |
| 66388099 | 4MX900 LED40S/840 PSD MB WH L1200 | LED40S |
| 66389799 | 4MX900 LED40S/840 PSD NB WH L1200 | LED40S |
| 66390399 | 4MX900 LED40S/840 PSD DA20 WH L1200 | LED40S |
| 66444399 | 4MX900 LED60S/840 PSD WB WH L1800 | LED60S |
| 66445099 | 4MX900 LED60S/840 PSD MB WH L1800 | LED60S |
| 66446799 | 4MX900 LED60S/840 PSD NB WH L1800 | LED60S |
| 66447499 | 4MX900 LED60S/840 PSD DA20 WH L1800 | LED60S |
| 66460399 | 4MX900 LED90S/840 PSD WB WH L1800 | LED90S |
| 66461099 | 4MX900 LED90S/840 PSD MB WH L1800 | LED90S |
| 66462799 | 4MX900 LED90S/840 PSD NB WH L1800 | LED90S |
| 66463499 | 4MX900 LED90S/840 PSD DA20 WH L1800 | LED90S |
| 66476499 | 4MX900 581 LED40S/840 PSU WB WH | LED40S |
| 66477199 | 4MX900 581 LED40S/840 PSU MB WH | LED40S |
| 66492499 | 4MX900 491 LED40S/840 PSU WB WH | LED40S |
| 66493199 | 4MX900 491 LED40S/840 PSU MB WH | LED40S |
| 66612699 | 4MX900 LED40S/840 PSU WB WH L1200 | LED40S |
| 66624999 | 4MX900 491 LED40S/840 PSD WB WH | LED40S |
| 66625699 | 4MX900 491 LED40S/840 PSD MB WH | LED40S |
| 66626399 | 4MX900 491 LED40S/840 PSD NB WH | LED40S |
| 66628799 | 4MX900 491 LED50S/840 PSD WB WH | LED50S |
| 66629499 | 4MX900 491 LED50S/840 PSD MB WH | LED50S |
| 66630099 | 4MX900 491 LED50S/840 PSD NB WH | LED50S |
| 66631799 | 4MX900 491 LED50S/840 PSD DA20 WH | LED50S |
| 66633199 | 4MX900 LED40S/840 PSD A30 WH L1200 | LED40S |
| 66635599 | 4MX900 LED60S/840 PSD A30 WH L1800 | LED60S |
| 66636299 | 4MX900 581 LED40S/840 PSU A30 WH | LED40S |
| 66637999 | 4MX900 581 LED50S/840 PSU A30 WH | LED50S |
| 66638699 | 4MX900 491 LED40S/840 PSU A30 WH | LED40S |
| 66639399 | 4MX900 491 LED50S/840 PSU A30 WH | LED50S |
| 66640999 | 4MX900 581 LED50S/840 PSU WB WH | LED50S |
| 66641699 | 4MX900 581 LED50S/840 PSU MB WH | LED50S |
| 66644799 | 4MX900 491 LED50S/840 PSU WB WH | LED50S |
| 66645499 | 4MX900 491 LED50S/840 PSU MB WH | LED50S |
| 66646199 | 4MX900 491 LED50S/840 PSU NB WH | LED50S |
| 66681299 | 4MX900 LED90S/840 PSD A30 WH L1800 | LED90S |
| 66790199 | 4MX900 491 LED75S/840 PSU WB WH | LED75S |
| 66800799 | 4MX900 491 LED75S/840 PSD WB WH | LED75S |
| 66801499 | 4MX900 491 LED75S/840 PSD MB WH | LED75S |
| 66805299 | 4MX900 491 LED75S/840 PSD A30 WH | LED75S |
| 66436899 | 4MX900 LED60S/840 PSD WB SI L1800 | LED60S |
| 66439999 | 4MX900 LED60S/840 PSD DA20 SI L1800 | LED60S |
| 66452899 | 4MX900 LED90S/840 PSD WB SI L1800 | LED90S |
| 66453599 | 4MX900 LED90S/840 PSD MB SI L1800 | LED90S |
| 66484999 | 4MX900 491 LED40S/840 PSU WB SI | LED40S |

## Date tehnice lumină

# Maxos LED Performer

| Order Code | Full Product Name | Randament luminos (nominal) (nom.) | Flux luminos | Tip de sistem optic |
|---|---|---|---|---|
| 66387399 | 4MX900 LED40S/840 PSD WB WH L1200 | 154 lm/W | 4.000 lm | Fascicul luminos larg |
| 66388099 | 4MX900 LED40S/840 PSD MB WH L1200 | 154 lm/W | 4.000 lm | Fascicul luminos mediu |
| 66389799 | 4MX900 LED40S/840 PSD NB WH L1200 | 154 lm/W | 4.000 lm | Fascicul luminos îngust |
| 66390399 | 4MX900 LED40S/840 PSD DA20 WH L1200 | 154 lm/W | 4.000 lm | Sistem optic dublu asimetric de 20° |
| 66444399 | 4MX900 LED60S/840 PSD WB WH L1800 | 161 lm/W | 6.000 lm | Fascicul luminos larg |
| 66445099 | 4MX900 LED60S/840 PSD MB WH L1800 | 161 lm/W | 6.000 lm | Fascicul luminos mediu |
| 66446799 | 4MX900 LED60S/840 PSD NB WH L1800 | 161 lm/W | 6.000 lm | Fascicul luminos îngust |
| 66447499 | 4MX900 LED60S/840 PSD DA20 WH L1800 | 161 lm/W | 6.000 lm | Sistem optic dublu asimetric de 20° |
| 66460399 | 4MX900 LED90S/840 PSD WB WH L1800 | 150 lm/W | 9.000 lm | Fascicul luminos larg |
| 66461099 | 4MX900 LED90S/840 PSD MB WH L1800 | 150 lm/W | 9.000 lm | Fascicul luminos mediu |
| 66462799 | 4MX900 LED90S/840 PSD NB WH L1800 | 150 lm/W | 9.000 lm | Fascicul luminos îngust |
| 66463499 | 4MX900 LED90S/840 PSD DA20 WH L1800 | 150 lm/W | 9.000 lm | Sistem optic dublu asimetric de 20° |
| 66476499 | 4MX900 581 LED40S/840 PSU WB WH | 159 lm/W | 4.000 lm | Fascicul luminos larg |
| 66477199 | 4MX900 581 LED40S/840 PSU MB WH | 159 lm/W | 4.000 lm | Fascicul luminos mediu |
| 66492499 | 4MX900 491 LED40S/840 PSU WB WH | 159 lm/W | 4.000 lm | Fascicul luminos larg |
| 66493199 | 4MX900 491 LED40S/840 PSU MB WH | 159 lm/W | 4.000 lm | Fascicul luminos mediu |
| 66612699 | 4MX900 LED40S/840 PSU WB WH L1200 | 154 lm/W | 4.000 lm | Fascicul luminos larg |
| 66624999 | 4MX900 491 LED40S/840 PSD WB WH | 159 lm/W | 4.000 lm | Fascicul luminos larg |
| 66625699 | 4MX900 491 LED40S/840 PSD MB WH | 159 lm/W | 4.000 lm | Fascicul luminos mediu |
| 66626399 | 4MX900 491 LED40S/840 PSD NB WH | 159 lm/W | 4.000 lm | Fascicul luminos îngust |
| 66628799 | 4MX900 491 LED50S/840 PSD WB WH | 155 lm/W | 5.000 lm | Fascicul luminos larg |
| 66629499 | 4MX900 491 LED50S/840 PSD MB WH | 155 lm/W | 5.000 lm | Fascicul luminos mediu |
| 66630099 | 4MX900 491 LED50S/840 PSD NB WH | 155 lm/W | 5.000 lm | Fascicul luminos îngust |
| 66631799 | 4MX900 491 LED50S/840 PSD DA20 WH | 155 lm/W | 5.000 lm | Sistem optic dublu asimetric de 20° |
| 66633199 | 4MX900 LED40S/840 PSD A30 WH L1200 | 154 lm/W | 4.000 lm | Axă asimetrică în oglindă cu unghi de 30º |
| 66635599 | 4MX900 LED60S/840 PSD A30 WH L1800 | 161 lm/W | 6.000 lm | Axă asimetrică în oglindă cu unghi de 30º |
| 66636299 | 4MX900 581 LED40S/840 PSU A30 WH | 159 lm/W | 4.000 lm | Axă asimetrică în oglindă cu unghi de 30º |
| 66637999 | 4MX900 581 LED50S/840 PSU A30 WH | 155 lm/W | 5.000 lm | Axă asimetrică în oglindă cu unghi de 30º |
| 66638699 | 4MX900 491 LED40S/840 PSU A30 WH | 159 lm/W | 4.000 lm | Axă asimetrică în oglindă cu unghi de 30º |
| 66639399 | 4MX900 491 LED50S/840 PSU A30 WH | 155 lm/W | 5.000 lm | Axă asimetrică în oglindă cu unghi de 30º |
| 66640999 | 4MX900 581 LED50S/840 PSU WB WH | 155 lm/W | 5.000 lm | Fascicul luminos larg |
| 66641699 | 4MX900 581 LED50S/840 PSU MB WH | 155 lm/W | 5.000 lm | Fascicul luminos mediu |
| 66644799 | 4MX900 491 LED50S/840 PSU WB WH | 155 lm/W | 5.000 lm | Fascicul luminos larg |
| 66645499 | 4MX900 491 LED50S/840 PSU MB WH | 155 lm/W | 5.000 lm | Fascicul luminos mediu |
| 66646199 | 4MX900 491 LED50S/840 PSU NB WH | 155 lm/W | 5.000 lm | Fascicul luminos îngust |
| 66681299 | 4MX900 LED90S/840 PSD A30 WH L1800 | 150 lm/W | 9.000 lm | Axă asimetrică în oglindă cu unghi de 30º |

# Maxos LED Performer

| Order Code | Full Product Name | Randament luminos (nominal) (nom.) | Flux luminos | Tip de sistem optic |
|---|---|---|---|---|
| 66790199 | 4MX900 491 LED75S/840 PSU WB WH | 149 lm/W | 7.500 lm | Fascicul luminos larg |
| 66800799 | 4MX900 491 LED75S/840 PSD WB WH | 149 lm/W | 7.500 lm | Fascicul luminos larg |
| 66801499 | 4MX900 491 LED75S/840 PSD MB WH | 149 lm/W | 7.500 lm | Fascicul luminos mediu |
| 66805299 | 4MX900 491 LED75S/840 PSD A30 WH | 149 lm/W | 7.500 lm | Axă asimetrică în oglindă cu unghi de 30º |

| Order Code | Full Product Name | Randament luminos (nominal) (nom.) | Flux luminos | Tip de sistem optic |
|---|---|---|---|---|
| 66436899 | 4MX900 LED60S/840 PSD WB SI L1800 | 161 lm/W | 6.000 lm | Fascicul luminos larg |
| 66439999 | 4MX900 LED60S/840 PSD DA20 SI L1800 | 161 lm/W | 6.000 lm | Sistem optic dublu asimetric de 20° |
| 66452899 | 4MX900 LED90S/840 PSD WB SI L1800 | 150 lm/W | 9.000 lm | Fascicul luminos larg |
| 66453599 | 4MX900 LED90S/840 PSD MB SI L1800 | 150 lm/W | 9.000 lm | Fascicul luminos mediu |
| 66484999 | 4MX900 491 LED40S/840 PSU WB SI | 159 lm/W | 4.000 lm | Fascicul luminos larg |

## Funcţionare și sistem electric

| Order Code | Full Product Name | Consum de curent |
|---|---|---|
| 66387399 | 4MX900 LED40S/840 PSD WB WH L1200 | 25,9 W |
| 66388099 | 4MX900 LED40S/840 PSD MB WH L1200 | 25,9 W |
| 66389799 | 4MX900 LED40S/840 PSD NB WH L1200 | 25,9 W |
| 66390399 | 4MX900 LED40S/840 PSD DA20 WH L1200 | 25,9 W |
| 66444399 | 4MX900 LED60S/840 PSD WB WH L1800 | 37,3 W |
| 66445099 | 4MX900 LED60S/840 PSD MB WH L1800 | 37,3 W |
| 66446799 | 4MX900 LED60S/840 PSD NB WH L1800 | 37,3 W |
| 66447499 | 4MX900 LED60S/840 PSD DA20 WH L1800 | 37,3 W |
| 66460399 | 4MX900 LED90S/840 PSD WB WH L1800 | 60,1 W |
| 66461099 | 4MX900 LED90S/840 PSD MB WH L1800 | 60,1 W |
| 66462799 | 4MX900 LED90S/840 PSD NB WH L1800 | 60,1 W |
| 66463499 | 4MX900 LED90S/840 PSD DA20 WH L1800 | 60,1 W |
| 66476499 | 4MX900 581 LED40S/840 PSU WB WH | 25,2 W |
| 66477199 | 4MX900 581 LED40S/840 PSU MB WH | 25,2 W |
| 66492499 | 4MX900 491 LED40S/840 PSU WB WH | 25,2 W |
| 66493199 | 4MX900 491 LED40S/840 PSU MB WH | 25,2 W |
| 66612699 | 4MX900 LED40S/840 PSU WB WH L1200 | 25,9 W |
| 66624999 | 4MX900 491 LED40S/840 PSD WB WH | 25,2 W |
| 66625699 | 4MX900 491 LED40S/840 PSD MB WH | 25,2 W |
| 66626399 | 4MX900 491 LED40S/840 PSD NB WH | 25,2 W |
| 66628799 | 4MX900 491 LED50S/840 PSD WB WH | 32,2 W |
| 66629499 | 4MX900 491 LED50S/840 PSD MB WH | 32,2 W |
| 66630099 | 4MX900 491 LED50S/840 PSD NB WH | 32,2 W |

| Order Code | Full Product Name | Consum de curent |
|---|---|---|
| 66631799 | 4MX900 491 LED50S/840 PSD DA20 WH | 32,2 W |
| 66633199 | 4MX900 LED40S/840 PSD A30 WH L1200 | 25,9 W |
| 66635599 | 4MX900 LED60S/840 PSD A30 WH L1800 | 37,3 W |
| 66636299 | 4MX900 581 LED40S/840 PSU A30 WH | 25,2 W |
| 66637999 | 4MX900 581 LED50S/840 PSU A30 WH | 32,2 W |
| 66638699 | 4MX900 491 LED40S/840 PSU A30 WH | 25,2 W |
| 66639399 | 4MX900 491 LED50S/840 PSU A30 WH | 32,2 W |
| 66640999 | 4MX900 581 LED50S/840 PSU WB WH | 32,2 W |
| 66641699 | 4MX900 581 LED50S/840 PSU MB WH | 32,2 W |
| 66644799 | 4MX900 491 LED50S/840 PSU WB WH | 32,2 W |
| 66645499 | 4MX900 491 LED50S/840 PSU MB WH | 32,2 W |
| 66646199 | 4MX900 491 LED50S/840 PSU NB WH | 32,2 W |
| 66681299 | 4MX900 LED90S/840 PSD A30 WH L1800 | 60,1 W |
| 66790199 | 4MX900 491 LED75S/840 PSU WB WH | 50,2 W |
| 66800799 | 4MX900 491 LED75S/840 PSD WB WH | 50,2 W |
| 66801499 | 4MX900 491 LED75S/840 PSD MB WH | 50,2 W |
| 66805299 | 4MX900 491 LED75S/840 PSD A30 WH | 50,2 W |
| 66436899 | 4MX900 LED60S/840 PSD WB SI L1800 | 37,3 W |
| 66439999 | 4MX900 LED60S/840 PSD DA20 SI L1800 | 37,3 W |
| 66452899 | 4MX900 LED90S/840 PSD WB SI L1800 | 60,1 W |
| 66453599 | 4MX900 LED90S/840 PSD MB SI L1800 | 60,1 W |
| 66484999 | 4MX900 491 LED40S/840 PSU WB SI | 25,2 W |

## Sisteme de comandă și reglarea intensităţii luminoase

| Order Code | Full Product Name | Cu reglarea intensităţii luminoase |
|---|---|---|
| 66387399 | 4MX900 LED40S/840 PSD WB WH L1200 | Da |
| 66388099 | 4MX900 LED40S/840 PSD MB WH L1200 | Da |
| 66389799 | 4MX900 LED40S/840 PSD NB WH L1200 | Da |
| 66390399 | 4MX900 LED40S/840 PSD DA20 WH L1200 | Da |
| 66444399 | 4MX900 LED60S/840 PSD WB WH L1800 | Da |

| Order Code | Full Product Name | Cu reglarea intensităţii luminoase |
|---|---|---|
| 66445099 | 4MX900 LED60S/840 PSD MB WH L1800 | Da |
| 66446799 | 4MX900 LED60S/840 PSD NB WH L1800 | Da |
| 66447499 | 4MX900 LED60S/840 PSD DA20 WH L1800 | Da |
| 66460399 | 4MX900 LED90S/840 PSD WB WH L1800 | Da |
| 66461099 | 4MX900 LED90S/840 PSD MB WH L1800 | Da |

# Maxos LED Performer

| Order Code | Full Product Name | Cu reglarea intensităţii luminoase |
|---|---|---|
| 66462799 | 4MX900 LED90S/840 PSD NB WH L1800 | Da |
| 66463499 | 4MX900 LED90S/840 PSD DA20 WH L1800 | Da |
| 66476499 | 4MX900 581 LED40S/840 PSU WB WH | Nu |
| 66477199 | 4MX900 581 LED40S/840 PSU MB WH | Nu |
| 66492499 | 4MX900 491 LED40S/840 PSU WB WH | Nu |
| 66493199 | 4MX900 491 LED40S/840 PSU MB WH | Nu |
| 66612699 | 4MX900 LED40S/840 PSU WB WH L1200 | Nu |
| 66624999 | 4MX900 491 LED40S/840 PSD WB WH | Da |
| 66625699 | 4MX900 491 LED40S/840 PSD MB WH | Da |
| 66626399 | 4MX900 491 LED40S/840 PSD NB WH | Da |
| 66628799 | 4MX900 491 LED50S/840 PSD WB WH | Da |
| 66629499 | 4MX900 491 LED50S/840 PSD MB WH | Da |
| 66630099 | 4MX900 491 LED50S/840 PSD NB WH | Da |
| 66631799 | 4MX900 491 LED50S/840 PSD DA20 WH | Da |
| 66633199 | 4MX900 LED40S/840 PSD A30 WH L1200 | Da |
| 66635599 | 4MX900 LED60S/840 PSD A30 WH L1800 | Da |
| 66636299 | 4MX900 581 LED40S/840 PSU A30 WH | Nu |
| 66637999 | 4MX900 581 LED50S/840 PSU A30 WH | Nu |

| Order Code | Full Product Name | Cu reglarea intensităţii luminoase |
|---|---|---|
| 66638699 | 4MX900 491 LED40S/840 PSU A30 WH | Nu |
| 66639399 | 4MX900 491 LED50S/840 PSU A30 WH | Nu |
| 66640999 | 4MX900 581 LED50S/840 PSU WB WH | Nu |
| 66641699 | 4MX900 581 LED50S/840 PSU MB WH | Nu |
| 66644799 | 4MX900 491 LED50S/840 PSU WB WH | Nu |
| 66645499 | 4MX900 491 LED50S/840 PSU MB WH | Nu |
| 66646199 | 4MX900 491 LED50S/840 PSU NB WH | Nu |
| 66681299 | 4MX900 LED90S/840 PSD A30 WH L1800 | Da |
| 66790199 | 4MX900 491 LED75S/840 PSU WB WH | Nu |
| 66800799 | 4MX900 491 LED75S/840 PSD WB WH | Da |
| 66801499 | 4MX900 491 LED75S/840 PSD MB WH | Da |
| 66805299 | 4MX900 491 LED75S/840 PSD A30 WH | Da |
| 66436899 | 4MX900 LED60S/840 PSD WB SI L1800 | Da |
| 66439999 | 4MX900 LED60S/840 PSD DA20 SI L1800 | Da |
| 66452899 | 4MX900 LED90S/840 PSD WB SI L1800 | Da |
| 66453599 | 4MX900 LED90S/840 PSD MB SI L1800 | Da |
| 66484999 | 4MX900 491 LED40S/840 PSU WB SI | Nu |

## Sistem mecanic și carcasă

| Order Code | Full Product Name | Culoare carcasă |
|---|---|---|
| 66387399 | 4MX900 LED40S/840 PSD WB WH L1200 | Alb |
| 66388099 | 4MX900 LED40S/840 PSD MB WH L1200 | Alb |
| 66389799 | 4MX900 LED40S/840 PSD NB WH L1200 | Alb |
| 66390399 | 4MX900 LED40S/840 PSD DA20 WH L1200 | Alb |
| 66444399 | 4MX900 LED60S/840 PSD WB WH L1800 | Alb |
| 66445099 | 4MX900 LED60S/840 PSD MB WH L1800 | Alb |
| 66446799 | 4MX900 LED60S/840 PSD NB WH L1800 | Alb |
| 66447499 | 4MX900 LED60S/840 PSD DA20 WH L1800 | Alb |
| 66460399 | 4MX900 LED90S/840 PSD WB WH L1800 | Alb |
| 66461099 | 4MX900 LED90S/840 PSD MB WH L1800 | Alb |
| 66462799 | 4MX900 LED90S/840 PSD NB WH L1800 | Alb |
| 66463499 | 4MX900 LED90S/840 PSD DA20 WH L1800 | Alb |
| 66476499 | 4MX900 581 LED40S/840 PSU WB WH | Alb |
| 66477199 | 4MX900 581 LED40S/840 PSU MB WH | Alb |
| 66492499 | 4MX900 491 LED40S/840 PSU WB WH | Alb |
| 66493199 | 4MX900 491 LED40S/840 PSU MB WH | Alb |
| 66612699 | 4MX900 LED40S/840 PSU WB WH L1200 | Alb |
| 66624999 | 4MX900 491 LED40S/840 PSD WB WH | Alb |
| 66625699 | 4MX900 491 LED40S/840 PSD MB WH | Alb |
| 66626399 | 4MX900 491 LED40S/840 PSD NB WH | Alb |
| 66628799 | 4MX900 491 LED50S/840 PSD WB WH | Alb |
| 66629499 | 4MX900 491 LED50S/840 PSD MB WH | Alb |
| 66630099 | 4MX900 491 LED50S/840 PSD NB WH | Alb |

| Order Code | Full Product Name | Culoare carcasă |
|---|---|---|
| 66631799 | 4MX900 491 LED50S/840 PSD DA20 WH | Alb |
| 66633199 | 4MX900 LED40S/840 PSD A30 WH L1200 | Alb |
| 66635599 | 4MX900 LED60S/840 PSD A30 WH L1800 | Alb |
| 66636299 | 4MX900 581 LED40S/840 PSU A30 WH | Alb |
| 66637999 | 4MX900 581 LED50S/840 PSU A30 WH | Alb |
| 66638699 | 4MX900 491 LED40S/840 PSU A30 WH | Alb |
| 66639399 | 4MX900 491 LED50S/840 PSU A30 WH | Alb |
| 66640999 | 4MX900 581 LED50S/840 PSU WB WH | Alb |
| 66641699 | 4MX900 581 LED50S/840 PSU MB WH | Alb |
| 66644799 | 4MX900 491 LED50S/840 PSU WB WH | Alb |
| 66645499 | 4MX900 491 LED50S/840 PSU MB WH | Alb |
| 66646199 | 4MX900 491 LED50S/840 PSU NB WH | Alb |
| 66681299 | 4MX900 LED90S/840 PSD A30 WH L1800 | Alb |
| 66790199 | 4MX900 491 LED75S/840 PSU WB WH | Alb |
| 66800799 | 4MX900 491 LED75S/840 PSD WB WH | Alb |
| 66801499 | 4MX900 491 LED75S/840 PSD MB WH | Alb |
| 66805299 | 4MX900 491 LED75S/840 PSD A30 WH | Alb |
| 66436899 | 4MX900 LED60S/840 PSD WB SI L1800 | Argintiu |
| 66439999 | 4MX900 LED60S/840 PSD DA20 SI L1800 | Argintiu |
| 66452899 | 4MX900 LED90S/840 PSD WB SI L1800 | Argintiu |
| 66453599 | 4MX900 LED90S/840 PSD MB SI L1800 | Argintiu |
| 66484999 | 4MX900 491 LED40S/840 PSU WB SI | Argintiu |


## Condiţii de utilizare

# Maxos LED Performer


| Order Code | Full Product Name | Nivel maxim de reglare a intensității luminoase |
|---|---|---|
| 66387399 | 4MX900 LED40S/840 PSD WB WH L1200 | 1% |
| 66388099 | 4MX900 LED40S/840 PSD MB WH L1200 | 1% |
| 66389799 | 4MX900 LED40S/840 PSD NB WH L1200 | 1% |
| 66390399 | 4MX900 LED40S/840 PSD DA20 WH L1200 | 1% |
| 66444399 | 4MX900 LED60S/840 PSD WB WH L1800 | 1% |
| 66445099 | 4MX900 LED60S/840 PSD MB WH L1800 | 1% |
| 66446799 | 4MX900 LED60S/840 PSD NB WH L1800 | 1% |
| 66447499 | 4MX900 LED60S/840 PSD DA20 WH L1800 | 1% |
| 66460399 | 4MX900 LED90S/840 PSD WB WH L1800 | 1% |
| 66461099 | 4MX900 LED90S/840 PSD MB WH L1800 | 1% |
| 66462799 | 4MX900 LED90S/840 PSD NB WH L1800 | 1% |
| 66463499 | 4MX900 LED90S/840 PSD DA20 WH L1800 | 1% |
| 66476499 | 4MX900 581 LED40S/840 PSU WB WH | Nu se aplică |
| 66477199 | 4MX900 581 LED40S/840 PSU MB WH | Nu se aplică |
| 66492499 | 4MX900 491 LED40S/840 PSU WB WH | Nu se aplică |
| 66493199 | 4MX900 491 LED40S/840 PSU MB WH | Nu se aplică |
| 66612699 | 4MX900 LED40S/840 PSU WB WH L1200 | Nu se aplică |
| 66624999 | 4MX900 491 LED40S/840 PSD WB WH | 1% |
| 66625699 | 4MX900 491 LED40S/840 PSD MB WH | 1% |
| 66626399 | 4MX900 491 LED40S/840 PSD NB WH | 1% |
| 66628799 | 4MX900 491 LED50S/840 PSD WB WH | 1% |
| 66629499 | 4MX900 491 LED50S/840 PSD MB WH | 1% |
| 66630099 | 4MX900 491 LED50S/840 PSD NB WH | 1% |

| Order Code | Full Product Name | Nivel maxim de reglare a intensității luminoase |
|---|---|---|
| 66631799 | 4MX900 491 LED50S/840 PSD DA20 WH | 1% |
| 66633199 | 4MX900 LED40S/840 PSD A30 WH L1200 | 1% |
| 66635599 | 4MX900 LED60S/840 PSD A30 WH L1800 | 1% |
| 66636299 | 4MX900 581 LED40S/840 PSU A30 WH | Nu se aplică |
| 66637999 | 4MX900 581 LED50S/840 PSU A30 WH | Nu se aplică |
| 66638699 | 4MX900 491 LED40S/840 PSU A30 WH | Nu se aplică |
| 66639399 | 4MX900 491 LED50S/840 PSU A30 WH | Nu se aplică |
| 66640999 | 4MX900 581 LED50S/840 PSU WB WH | Nu se aplică |
| 66641699 | 4MX900 581 LED50S/840 PSU MB WH | Nu se aplică |
| 66644799 | 4MX900 491 LED50S/840 PSU WB WH | Nu se aplică |
| 66645499 | 4MX900 491 LED50S/840 PSU MB WH | Nu se aplică |
| 66646199 | 4MX900 491 LED50S/840 PSU NB WH | Nu se aplică |
| 66681299 | 4MX900 LED90S/840 PSD A30 WH L1800 | 1% |
| 66790199 | 4MX900 491 LED75S/840 PSU WB WH | Nu se aplică |
| 66800799 | 4MX900 491 LED75S/840 PSD WB WH | 1% |
| 66801499 | 4MX900 491 LED75S/840 PSD MB WH | 1% |
| 66805299 | 4MX900 491 LED75S/840 PSD A30 WH | 1% |
| 66436899 | 4MX900 LED60S/840 PSD WB SI L1800 | 1% |
| 66439999 | 4MX900 LED60S/840 PSD DA20 SI L1800 | 1% |
| 66452899 | 4MX900 LED90S/840 PSD WB SI L1800 | 1% |
| 66453599 | 4MX900 LED90S/840 PSD MB SI L1800 | 1% |
| 66484999 | 4MX900 491 LED40S/840 PSU WB SI | Nu se aplică |


## Polar Wide Diagrams




**IFPS_4MX900 491 1xLED40S/830 PSD A30-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED40S/830 PSD DA20-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED40S/830 PSD MB-Polar Normal (separate)**


## Polar Wide Diagrams





**IFPS_4MX900 491 1xLED40S/830 PSD WB-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED40S/830 PSU MB-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED40S/830 PSU NB-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED40S/830 PSU WB-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED40S/840 PSD A30-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED40S/840 PSD DA20-Polar Normal (separate)**




**IFPS_4MX900 491 1xLED40S/840 PSD WB-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED40S/840 PSU A30-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED40S/840 PSU MB-Polar Normal (separate)**


## Polar Wide Diagrams





**IFPS_4MX900 491 1xLED40S/840 PSU WB-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED50S/830 PSD A30-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED50S/830 PSD DA20-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED50S/830 PSD MB-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED50S/830 PSD WB-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED50S/830 PSU NB-Polar Normal (separate)**




**IFPS_4MX900 491 1xLED50S/830 PSU WB-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED50S/840 PSD DA20-Polar Normal (separate)**





**IFPS_4MX900 491 1xLED50S/840 PSD WB-Polar Normal (separate)**


## Polar Wide Diagrams





IFPS_4MX900 491 1xLED50S/840 PSU A30-Polar Normal (separate)





IFPS_4MX900 491 1xLED50S/840 PSU NB-Polar Normal (separate)





IFPS_4MX900 491 1xLED71S/830 PSD A30-Polar Normal (separate)





IFPS_4MX900 491 1xLED71S/830 PSD MB-Polar Normal (separate)





IFPS_4MX900 491 1xLED71S/830 PSD NB-Polar Normal (separate)





IFPS_4MX900 491 1xLED71S/830 PSD WB-Polar Normal (separate)




IFPS_4MX900 491 1xLED71S/830 PSU A30-Polar Normal (separate)





IFPS_4MX900 491 1xLED75S/840 PSD A30-Polar Normal (separate)





IFPS_4MX900 491 1xLED75S/840 PSD DA20-Polar Normal (separate)


## Polar Wide Diagrams





IFPS_4MX900 491 1xLED75S/840 PSD WB-Polar Normal (separate)





IFPS_4MX900 491 1xLED75S/840 PSU WB-Polar Normal (separate)





IFPS_4MX900 581 1xLED40S/830 PSU MB-Polar Normal (separate)





IFPS_4MX900 581 1xLED40S/830 PSU WB-Polar Normal (separate)





IFPS_4MX900 581 1xLED40S/840 PSU A30-Polar Normal (separate)





IFPS_4MX900 581 1xLED40S/840 PSU WB-Polar Normal (separate)




IFPS_4MX900 581 1xLED50S/830 PSU WB-Polar Normal (separate)





IFPS_4MX900 581 1xLED50S/840 PSU MB-Polar Normal (separate)





IFPS_4MX900 581 1xLED75S/840 PSU A30-Polar Normal (separate)


## Polar Wide Diagrams





IFPS_4MX900 L1200 1xLED32S/840 PSU WB-Polar Normal (separate)





IFPS_4MX900 L1200 1xLED40S/830 PSU WB-Polar Normal (separate)





IFPS_4MX900 L1200 1xLED40S/840 PSU WB-Polar Normal (separate)





IFPS_4MX900 L1200 1xLED57S/830 PSD MB-Polar Normal (separate)





IFPS_4MX900 L1200 1xLED57S/830 PSD NB-Polar Normal (separate)





IFPS_4MX900 L1200 1xLED57S/830 PSD WB-Polar Normal (separate)




IFPS_4MX900 L1200 1xLED57S/830 PSU WB-Polar Normal (separate)





IFPS_4MX900 L1200 1xLED60S/840 PSD DA20-Polar Normal (separate)





IFPS_4MX900 L1200 1xLED60S/840 PSD NB-Polar Normal (separate)


## Polar Wide Diagrams





**IFPS_4MX900 L1200 1xLED60S/840 PSD WB-Polar Normal (separate)**





**IFPS_4MX900 L1800 1xLED48S/830 PSD NB-Polar Normal (separate)**





**IFPS_4MX900 L1800 1xLED48S/840 PSD DA20-Polar Normal (separate)**





**IFPS_4MX900 L1800 1xLED48S/840 PSD NB-Polar Normal (separate)**





**IFPS_4MX900 L1800 1xLED48S/840 PSD WB-Polar Normal (separate)**





**IFPS_4MX900 L1800 1xLED60S/830 PSD A30-Polar Normal (separate)**




**IFPS_4MX900 L1800 1xLED60S/830 PSD MB-Polar Normal (separate)**





**IFPS_4MX900 L1800 1xLED60S/830 PSD NB-Polar Normal (separate)**





**IFPS_4MX900 L1800 1xLED60S/840 PSD DA20-Polar Normal (separate)**


## Polar Wide Diagrams





IFPS_4MX900 L1800 1xLED60S/840 PSD MB-Polar Normal (separate)





IFPS_4MX900 L1800 1xLED60S/840 PSD NB-Polar Normal (separate)





IFPS_4MX900 L1800 1xLED85S/830 PSD A30-Polar Normal (separate)





IFPS_4MX900 L1800 1xLED85S/830 PSD MB-Polar Normal (separate)





IFPS_4MX900 L1800 1xLED85S/830 PSD WB-Polar Normal (separate)





IFPS_4MX900 L1800 1xLED90S/840 PSD DA20-Polar Normal (separate)




IFPS_4MX900 L1800 1xLED90S/840 PSD NB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED40S/830 PSD A30-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED40S/830 PSD DA20-Polar Normal (separate)


## Polar Wide Diagrams





IFPS_4MX900 G3 491 1xLED40S/830 PSD MB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED40S/830 PSD NB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED40S/830 PSU A30-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED40S/830 PSU NB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED40S/830 PSU WB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED40S/840 PSD A30-Polar Normal (separate)




IFPS_4MX900 G3 491 1xLED40S/840 PSD DA20-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED40S/840 PSD NB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED40S/840 PSD WB-Polar Normal (separate)


## Polar Wide Diagrams





**IFPS_4MX900 G3 491 1xLED40S/840 PSU MB-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED50S/830 PSD A30-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED50S/830 PSD DA20-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED50S/830 PSD NB-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED50S/830 PSD WB-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED50S/830 PSU NB-Polar Normal (separate)**




**IFPS_4MX900 G3 491 1xLED50S/830 PSU WB-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED50S/840 PSD DA20-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED50S/840 PSD MB-Polar Normal (separate)**


## Polar Wide Diagrams





IFPS_4MX900 G3 491 1xLED50S/840 PSD NB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED50S/840 PSD WB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED50S/840 PSU A30-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED50S/840 PSU MB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED50S/840 PSU NB-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED50S/840 PSU WB-Polar Normal (separate)




IFPS_4MX900 G3 491 1xLED71S/830 PSD A30-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED71S/830 PSD DA20-Polar Normal (separate)





IFPS_4MX900 G3 491 1xLED71S/830 PSU A30-Polar Normal (separate)


## Polar Wide Diagrams





**IFPS_4MX900 G3 491 1xLED75S/840 PSD A30-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED75S/840 PSD MB-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED75S/840 PSD WB-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED75S/840 PSU A30-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED75S/840 PSU MB-Polar Normal (separate)**





**IFPS_4MX900 G3 491 1xLED75S/840 PSU NB-Polar Normal (separate)**




**IFPS_4MX900 G3 581 1xLED40S/840 PSU A30-Polar Normal (separate)**





**IFPS_4MX900 G3 581 1xLED40S/840 PSU MB-Polar Normal (separate)**





**IFPS_4MX900 G3 581 1xLED40S/840 PSU WB-Polar Normal (separate)**


## Polar Wide Diagrams





IFPS_4MX900 G3 581 1xLED50S/830 PSU A30-Polar Normal (separate)





IFPS_4MX900 G3 581 1xLED50S/830 PSU MB-Polar Normal (separate)





IFPS_4MX900 G3 581 1xLED50S/840 PSU MB-Polar Normal (separate)





IFPS_4MX900 G3 581 1xLED71S/830 PSU MB-Polar Normal (separate)





IFPS_4MX900 G3 581 1xLED75S/840 PSU A30-Polar Normal (separate)





IFPS_4MX900 G3 581 1xLED75S/840 PSU MB-Polar Normal (separate)




IFPS_4MX900 G3 581 1xLED75S/840 PSU WB-Polar Normal (separate)





IFPS_4MX900 G3 L1200 1xLED40S/830 PSD NB-Polar Normal (separate)





IFPS_4MX900 G3 L1200 1xLED40S/840 PSU WB-Polar Normal (separate)


## Polar Wide Diagrams





**IFPS_4MX900 G3 L1200 1xLED60S/840 PSU**
**WB-Polar Normal (separate)**





**IFPS_4MX900 G3 L1800 1xLED60S/830 PSD**
**NB-Polar Normal (separate)**





**IFPS_4MX900 G3 L1800 1xLED60S/830 PSD**
**WB-Polar Normal (separate)**





**IFPS_4MX900 G3 L1800 1xLED60S/840 PSD**
**MB-Polar Normal (separate)**





**IFPS_4MX900 G3 L1800 1xLED60S/840 PSD**
**NB-Polar Normal (separate)**




**IFPS_4MX900 G3 L1800 1xLED60S/840 PSD**
**WB-Polar Normal (separate)**




**IFPS_4MX900 G3 L1800 1xLED85S/830 PSD**
**WB-Polar Normal (separate)**




**IFPS_4MX900 G3 L1800 1xLED90S/840 PSD**
**NB-Polar Normal (separate)**

# Maxos LED Performer

© 2023 Signify Holding Toate drepturile rezervate. Signify nu oferă nicio reprezentare sau garanție în privința preciziei informațiilor incluse prin prezenta și nu poate purta responsabilitatea niciunei acțiuni corelate. Informațiile prezentate în acest document nu sunt menite să fie oferte comerciale sau să facă parte dintr-o ofertă sau un contract, în afara cazului în care Signify consimte altceva. Toate mărcile comerciale sunt deținute de Signify Holding sau de proprietarii respectivi.

www.lighting.philips.com
2023, Octombrie 24 - Informatie ce poate fi modificată