



High-perfomance ballasts for residential and commercial applications

AmbiStar

Ambistar electronic ballasts are an easy-to-install, energy-efficient replacement solution for optimizing residential and hospitality lighting.

Benefits

- Compliant with California Title 24 and DOE efficiency requirements
- Quick, flicker-free starting
- $\boldsymbol{\cdot}$ Easy to install in existing fixtures

Features

- FCC Class B EMI Rating, an EPA Energy Star requirement
- Efficient electronic circuitry
- \cdot Lamp ignition in less than 1 second
- \cdot Standard mounting footprints

Application

- \cdot Residential
- Hospitality

AmbiStar

Versions






RELB2S40N35I

REB4P32SC35M

Dimensional drawing



| Product | A1 | A2 | B1 | C1 |
|-----------------------|---------|---------|---------|---------|
| AMBISTAR REB2P32N35M | 9.5 in | 8.9 in | 1.3 in | 1.0 in |
| AMBISTAR REB4P32SC35M | 9.5 in | 8.90 in | 1.7 in | 1.18 in |
| AMBISTAR RELB2S40N35M | 9.50 in | 8.90 in | 1.30 in | 1.00 in |
| AMBISTAR RELB2S40N35I | 9.50 in | 8.90 in | 1.30 in | 1.00 in |
| | | | | |

| Operating and Electrical | |
|--------------------------|-------|
| Input Frequency | 60 Hz |
| Input Voltage | 120 V |

Operating and Electrical

| | | Total Harmonic Distortion |
|--------------|--------------------------------------|---------------------------|
| Order Code | Full Product Name | USA |
| 913701218101 | AMBISTAR ELE BALLAST (2) F40T12 120V | 20 % |
| 913701218102 | AMBISTAR ELE BALLAST (2) F40T12 120V | 20 % |

| | | Total Harmonic Distortion |
|--------------|-------------------------------------|---------------------------|
| Order Code | Full Product Name | USA |
| 913710850402 | AMBISTAR ELE BALLAST (2) F32T8 120V | 150 % |
| 913710221502 | AMBISTAR ELE BALLAST (4) F32T8 120V | 125 % |

General Information

| Order Code | Full Product Name | Number Of Lamps | Lamp Type | Order Code | Full Pro |
|--------------|---------------------------------|-----------------|-----------|--------------|----------|
| 913701218101 | AMBISTAR ELE BALLAST (2) F40T12 | 1/2 piece/unit | F40T12 | 913710850402 | AMBIS |
| | 120V | | | | 120V |
| 913701218102 | AMBISTAR ELE BALLAST (2) F40T12 | 1/2 piece/unit | F40T12 | 913710221502 | AMBIS |
| | 120V | | | | 120V |
| | | | | | |

| Order Code | Full Product Name | Number Of Lamps | Lamp Type |
|--------------|--------------------------------|-----------------|-----------|
| 913710850402 | AMBISTAR ELE BALLAST (2) F32T8 | 1/2 piece/unit | F32T8 |
| | 120V | | |
| 913710221502 | AMBISTAR ELE BALLAST (4) F32T8 | 3/4 piece/unit | F32T8 |
| | 120V | | |

Mechanical and Housing

AmbiStar

| Order Code | Full Product Name | Housing | Order Code | Full Product Name | Housing |
|--------------|--------------------------------------|---------|--------------|-------------------------------------|---------|
| 913701218101 | AMBISTAR ELE BALLAST (2) F40T12 120V | Ν | 913710850402 | AMBISTAR ELE BALLAST (2) F32T8 120V | Ν |
| 913701218102 | AMBISTAR ELE BALLAST (2) F40T12 120V | Ν | 913710221502 | AMBISTAR ELE BALLAST (4) F32T8 120V | SC |



© 2018 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2018, April 26 - data subject to change