



Faze 180 Concealed Emergency Unit

FX12L40W12

Concealed Emergency Unit, Lead Acid, 12V 40W, 16W Remote, 12W MR16, Xtest

The Faze 180 Series combines aesthetic appeal and architectural excellence. Designed to be the invisible emergency lighting unit utilizing a normal utility power circuit, so it can be controlled by a standard wall switch. With a superior mechanical design and unmatched electronics the Faze 180 is ideal for any design requiring a concealed lighting unit.

Product data

General Information		Order code	912400372493
Lamp Source Code	Incandescent	Local order code	.
Lamp Watts	12	Numerator - Quantity Per Pack	1
Number of Lamps	2	Numerator - Packs per outer box	1
Operating and Electrical		Material Nr. (12NC)	912400372493
Voltages	120/277 V	Net Weight (Piece)	13.600 kg
Maximum Lamp Watts	12	Commercial Code	FX12L40W12
Product Data		Catalog Number Description	Concealed Emergency Unit, Lead Acid, 12V 40W, 16W Remote, 12W MR16, Xtest
Order product name	FX12L40W12	Quick Ship	-
EAN/UPC - Product	781370853716		