



Faze 180 Concealed Emergency Unit

Concealed Emergency Unit, Lead Acid, 12V 100W, No Remote, 50W MR16, Xtest

Concealed Emergency Unit, Lead Acid, 12V 100W, No Remote, 50W MR16, Xtest

The Faze 180 Series combines aesthetic appeal and architectural excellence. Designed to be the invisible emergency lighting unit utilizing a normal utility power circuit, so it can be controlled by a standard wall switch. With a superior mechanical design and unmatched electronics the Faze 180 is ideal for any design requiring a concealed lighting unit.

Product data

General Information		EAN/UPC - Product 782343258385	
Lamp Source Code	Incandescent	Order code FX12L100W50	
Lamp Watts	50	Numerator - Quantity Per Pack 1	
Number of Lamps	2	Numerator - Packs per outer box 1	
Operating and Electrical		Material Nr. (12NC) 912401037943	
Voltages	120/277 V	Net Weight (Piece) 8.700 kg	
Maximum Lamp Watts	50	Catalog Number FX12L100W50	
Product Data		Catalog Number Description Concealed Emergency Unit, Lead Acid, 12V 100W, No Remote, 50W MR16, Xtest	
Order product name	FX12L100W50		