



# HID-Basic BHL for HPL/HPI

## BHL 250 K202 230V 50Hz BC2-126

Impregnated electromagnetic copper/iron ballasts for HPL and HPI (Plus) lamps

## **Product data**


Operating and Electrical					
Input Voltage	230 V				
Line Frequency	50 Hz				
Input Frequency	50 Hz				
Wiring					
Connector Type	Screw				
Approval and Application					
Approval Marks	CE marking ENEC certificate				
Product Data					
Order product name	BHL 250 K202-A2 230V 50Hz BC2-126				

Full product name	BHL 250 K202 230V 50Hz BC2-126
Full product code	872790094064000
Order code	94064000
Material Nr. (12NC)	913700283226
Numerator - Quantity Per Pack	1
EAN/UPC - Product/Case	8727900940640
Numerator - Packs per outer box	6
EAN/UPC - Case	8727900940657

Datasheet, 2023, April 30 data subject to change

# **HID-Basic BHL for HPL/HPI**

## Dimensional drawing



Product	D1	C1	A1	A2	B1
BHL 250 K202-A2 230V 50Hz	6.2 mm	65.0 mm	126.0 mm	104.0 mm	76.0 mm
BC2-126					



© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.