



# **SmartMate**

## SMARTMATE ELE BAL (2) 13W CFL (4-PIN) 120-277V KIT

Offering maximum versatility, the Philips Advance family of SmartMate ballasts for 4-pin compact fluorescent lamps drive a broad range of quad and triple-tube, circline, 2D, and long twin-tube lamps. SmartMate ballasts' energy efficient design, compact and lightweight housing, and user-friendly features make these ballasts an ideal choice for fixture manufacturers, retrofitters, and MRO replacement.

### **Product data**

General Information					
Lamp Type	CFQ13W/G24Q				
Number of Lamps	1/2 piece/unit				
Ballast Type	Electronic Fluorescent				
Base Model	ICF2S13H1LD				
Suitable For Outdoor Use	Yes				
Automatic Restart	Yes				
Operating and Electrical					
Input Voltage	120 to 277 V				
Input Frequency	50 to 60 Hz				
Total Harmonic Distortion USA	10 %				
Ignition Method	Programmed Start				
Crestfactor (Nom)	1.5				
Ignition Time (Nom)	1.5 s				
Ballast Factor (Nom)	1				
Power Factor (Nom)	0.98				
Input Current (Max)	0.25 A				
Input Current (Min)	0.11 A				
Input Power (Nom)	29-29 W				

Rated Lamp Power	13 W			
Wiring				
Color Input Terminals	Black and White			
Color Output Terminals				
· · ·	RED, YEL & BLU			
Wire Striplength	0.375 mm			
Lamp Connection	Series			
Wire Length by Color	No wires			
Wire Gauge (Nom)	18AWG mm			
Wire Type	Solid			
Remote Wiring Configuration Allowed	Yes			
Tandem Wiring Configuration Allowed	Yes			
Through Wiring Configuration Allowed	Yes			
Max Ballast-Lamp Distance Remote Wiring	1-L = 15' / 2-L = 6'			
Max Ballast-Lamp Distance Tandem Wiring 2-L: Red = 6'				
Max Ballast-Lamp Distance Through Wiring 2-L: Red = 6'				
Connector Type	Poke-In			
Temperature				
T-Case Maximum (Nom)	75 ℃			

## **SmartMate**

Mechanical and Housing					
Housing Material	Metal-Plastic				
Housing	H1				
Housing Dimensions	4.98" x 2.4" x 0.98"				
Approval and Application					
EMC Immunity Standard	FCC Non-Consumer				
Approval Marks	CSA certificate UL certificate CEC Listing				
	NOM certificate RoHS Compliant				
Hum And Noise Level	А				
UL Recognized	No				

SMARTMATE ELE BAL (2) 13W CFL (4-PIN)				
120-277V KIT				
781087117750				
913700500811				
1				
12				
913700500811				
0.250 kg				

## Dimensional drawing



Product	A1	A2	A3	B1	C1
SMARTMATE ELE BAL (2) 13W CFL (4-	4.60 in	4.20 in	2.00 in	3.00 in	1.29 in
PIN) 120-277V KIT					

#### ELE BAL (2) 13W CFL (4-PIN) 120-277V KIT



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.