



# Core & Coil (71A) MH ~LT~ 175W

## CORE & COIL HID MH BAL 100W M90/140 QUAD C&C

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

#### **Product data**

General Information	
ANSI Code	M90-M140
Lamp Type	100W MH
Number of Lamps	1 piece/unit
Circuit Type	HX-HPF
Ballast Type	Magnetic HID
Base Model	71A5390
Core Size	3 X 4 (2 LW)
Suitable For Outdoor Use	Yes
Ignitor Catalog Number	LI533-H4
Ignitor Temperature Rating	105°C
Capacitor Value	12 MFD
Capacitor Catalog Number	7C120M30RA
Capacitor Requirements	280V
Capacitor Temperature Rating	105°C
Capacitor Diameter/Oval	1.65 in
Dimensions	
Capacitor Height	2.75 in
Automatic Restart	No

120/208/240/277 V					
60 Hz					
2.5/1.5/1.3/1.12 A					
1.24/0.54/0.45/0.4 A 0.63-0.95/0.43-0.65/0.37-0.55/0.29-0.44 A 1.35-1.7 A 12%					
0.63-0.95/0.43-0.65/0.37-0.55/0.29-0.44 A					
1.35-1.7 A					
12%					
1					
0.90					
260 V					
1.15/0.66/0.58/0.5 A A					
129 W					
100 W					
0.5 mm					
12"					
Stranded					


Datasheet, 2019, February 12 data subject to change

### Core & Coil (71A) MH ~LT~ 175W

Remote Wiring Configuration	Yes
Allowed	
Max Ballast-Lamp Distance	20'
Remote Wiring	
Recommended Fuse Value	10/5/5/4 A
Approval and Application	
Open Circuit Voltage Test (Volts)	240-300 V
Approval Marks	ULR CSA certificate RoHS Compliant
Temperature Marking	B/B/A/A
UL Recognized	Yes
Hipot Test (1 Minute)	2000 V
Hipot Test (2 Seconds)	2500 V

UL Insulation Class	H(180°C)
UL Temperature Code	1029B
Product Data	
Order product name	CORE & COIL HID MH BAL 100W M90/140 QUAD C&C
EAN/UPC - Product	781087539057
Order code	913700502681
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	6
Material Nr. (12NC)	913700502681
Net Weight (Piece)	2.328 kg

#### Dimensional drawing



MH BAL 100W M90/140 QUAD KIT

Product	C1	C2	A1	A2	B1	B2
CORE & COIL HID 71A5390500D	3.07 in	1.5 in	3.9 in	3.5 in	2.8 in	2.4 in



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.