



# Core & Coil (71A) HPS ~LT~ 200W

# CORE & COIL HID HPS BAL 70W S62 120V C&C

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

#### **Product data**

General Information	
ANSI Code	S62
Lamp Type	70W HPS
Number of Lamps	1 piece/unit
Circuit Type	R-HPF
Ballast Type	Magnetic HID
Base Model	71А7907В
Core Size	2 5/8 x 2 3/16
Suitable For Outdoor Use	Yes
Ignitor Catalog Number	INTEGRAL
Ignitor Temperature Rating	125°C
Capacitor Value	28 MFD
Capacitor Catalog Number	7C280M12RA
Capacitor Requirements	120V
Capacitor Temperature Rating	105°C
Capacitor Diameter/Oval Dimensions	1.65 in
Capacitor Height	2.75 in
Automatic Restart	No
Operating and Electrical	
Input Voltage	120 V

Input Frequency	60 Hz	
Input Current (Open Circuit)	1.3 A	
Input Current (Starting)	0.9 A	
Input Current (Short Circuit)	1.9-2.9 A	
Secondary Short Circuit Current	1.9-2.9 A	
Constant Wattage Deviation	Within Trapezoid	
Ballast Factor (Nom)	1	
Power Factor (Nom)	0.90	
Open Circuit Voltage	120 V	
Input Current (Nom)	0.75 A A	
Input Power (Nom)	86 W	
Rated Lamp Power	70 W	
Wiring		
Wire Striplength	0.5 mm	
Wire Length by Color	12"	
Wire Type	Stranded	
Remote Wiring Configuration Allowed	Yes	
Max Ballast-Lamp Distance Remote Wiring 2'		
Recommended Fuse Value	3 A	

## Core & Coil (71A) HPS ~LT~ 200W

Approval and Application	
Open Circuit Voltage Test (Volts)	114-126 V
Approval Marks	ULR CSA certificate RoHS Compliant
Temperature Marking	А
UL Recognized	Yes
Hipot Test (1 Minute)	2000 V
Hipot Test (2 Seconds)	2500 V
UL Insulation Class	H(180°C)
UL Temperature Code	1029A

C&C


CORE & COIL HID HPS BAL 70W S62 120V

EAN/UPC - Product	781087790748
Order code	191924
Local order code	191924
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	16
Material Nr. (12NC)	913700525809
Net Weight (Piece)	0.994 kg


#### Product Data

Order product name

### **Dimensional drawing**



HPS BAL 70W S62 120V C&C





© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2019, February 12 - data subject to change