



Core & Coil (71A) MH ~LT~ 175W

CORE & COIL HID MH BAL 35/39W M130 120V C&C

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

General Information				
ANSI Code	M130			
Lamp Type	35/39W MH			
Number of Lamps	1 piece/unit			
Circuit Type	HX-HPF			
Ballast Type	Magnetic HID			
Base Model	71A5005P			
Core Size	2 X 4			
Suitable For Outdoor Use	Yes			
Ignitor Catalog Number	LI533-H4			
Ignitor Temperature Rating	105°C			
Capacitor Value	28 MFD			
Capacitor Catalog Number	7C280M12RA			
Capacitor Requirements	120V			
Capacitor Temperature Rating	105°C			
Capacitor Diameter/Oval Dimensions	1.65 in			
Capacitor Height	2.75 in			
Automatic Restart	No			

Operating and Electrical			
Input Voltage	120 V		
Input Frequency	60 Hz		
Input Current (Open Circuit)	1.1 A		
Input Current (Starting)	0.45 A		
Input Current (Short Circuit)	0.3-0.5 A		
Secondary Short Circuit Current	0.6-0.75 A		
Constant Wattage Deviation	10%		
Ballast Factor (Nom)	1		
Power Factor (Nom)	0.90		
Open Circuit Voltage	230 V		
Input Current (Nom)	0.5 A A		
Input Power (Nom)	55 W		
Rated Lamp Power	35/39 W		
Wiring			
Wire Striplength	0.5 mm		
Wire Length by Color	12"		
Wire Type	Stranded		
Remote Wiring Configuration Allowed	Yes		


Datasheet, 2019, February 12 data subject to change

Core & Coil (71A) MH ~LT~ 175W

Max Ballast-Lamp Distance Remote Wiring 15'				
Recommended Fuse Value	3 A			
Approval and Application				
Open Circuit Voltage Test (Volts)	205-255 V			
Approval Marks	ULR CSA certificate RoHS Compliant			
Temperature Marking	A			
UL Recognized	Yes			
Hipot Test (1 Minute)	2000 V			
Hipot Test (2 Seconds)	2500 V			
UL Insulation Class	H(180°C)			
UL Temperature Code	1029A			

Product Data				
Order product name	CORE & COIL HID MH BAL 35/39W M130			
	120V C&C			
EAN/UPC - Product	781087104972			
Order code	913700529409			
Numerator - Quantity Per Pack	1			
Numerator - Packs per outer box	12			
Material Nr. (12NC)	913700529409			
Net Weight (Piece)	1.166 kg			

Dimensional drawing



MH BAL 35/39W M130 120V C&C

Product	C1	C2	A1	B1
CORE & COIL HID 71A5005500DP	1.7 in	0.83 in	4.2 in	2.2 in

