



# e-Vision Low Wattage 20-150W

## E-VISION ELE MH BAL 39W M130/C179 120V 50/60HZ

Low frequency electronic HID ballasts such as the Philips Advance e-Vision line constantly measure and adjust the wattage, optimizing delivery of the ceramic lamps' superior color properties. This makes ceramic metal halide operated by e-Vision ballasts the premier choice for many applications previously illuminated by either tungsten halogen or incandescent sources, such as retail lighting.

#### **Product data**

General Information				
ANSI Code	C130-M130,C179			
Lamp Type	39W MH			
Number of Lamps	1 piece/unit			
Ballast Type	Electronic HID			
Base Model	RMH39KBLS			
Suitable For Outdoor Use	Yes			
Operating and Electrical				
Input Voltage	120 V			
Input Frequency	50 to 60 Hz			
Max THD	15 %			
Lamp Current Crest Factor (Nom)	1.8			
Ignition Time (Nom)	1200 s			
Ballast Factor (Nom)	1			
Power Factor (Nom)	0.90			
Input Current (Operating) (Max)	0.4 A			
Input Current (Operating) (Min)	0.4 A			

Input Power (Nom)	45 W
Rated Lamp Watts	39 W
Wiring	
Color Input Terminals	No terminals
Color Output Terminals	No terminals
Wire Striplength	0.50 mm
Control Wire Gauge	NA
Wire Length by Color	All leads = 6"
Wire Gauge (Nom)	18AWG mm
Wire Type	Stranded
Remote Wiring Configuration Allowed	Yes
Tandem Wiring Configuration Allowed	No
Through Wiring Configuration Allowed	No
Connector Type	No connector


Datasheet, 2019, March 22 data subject to change

### e-Vision Low Wattage 20-150W

Temperature						
T-Case Maximum (Nom)	90 ℃					
Mechanical and Housing						
Housing Material	Metal					
Housing	К					
Housing Dimensions	4.1" × 1.3" × 1.2"					
Approval and Application						
EMC Immunity Standard	FCC Non-Consumer					
Approbation Marks	CSA certificate UL certificate RoHS Compliant					
Sound Rating	A					
UL Recognized	No					

E-VISION ELE MH BAL 39W M130/C179 120V			
50/60HZ			
781087073193			
RMH39KBLSM			
1			
12			
913700639089			
196.000 g			

#### Dimensional drawing



Product	A1	A2	А3	B1	B2	C1
E-VISION ELE MH BAL 39W M130/C179	4.4 in	4.1 in	4.5 in	1.1 in	0.5 in	1.2 in
120V 50/60HZ						



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.