

# BTA EM ballasts for TL Fluorescent lamps

## BTA 18W 230V C SC

This efficient, reliable, long-life electromagnetic ballast for TL-D fluorescent lamps features a balanced combination of essential characteristics, thus allowing a wide variety of standard applications.


### Product data

Operating and Electrical	
Input Voltage	230 V
Line Frequency	50 Hz
Input Frequency	50 Hz
Wiring	
Connector Type	Screw
Mechanical and Housing	
Housing	L 155x39x28
Approval and Application	
Energy Efficiency Index	C
Approval Marks	CE marking

Product Data	
Order product name	BTA 18W 230V C SC
Full product name	BTA 18W 230V C SC
Full product code	871016303364830
Order code	03364830
Material Nr. (12NC)	913710111750
Numerator - Quantity Per Pack	1
EAN/UPC - Product/Case	8710163148632
Numerator - Packs per outer box	32
EAN/UPC - Case	8710163033655

# BTA EM ballasts for TL Fluorescent lamps

## Dimensional drawing



Product	D1	C1	C3	A1	A2	A3	A4	B1	B2
BTA 18W	4.0	28.0	1.2	155.0	140.0	48.0	56.0	39.0	20.0
230V C SC	mm	mm	mm	mm	mm	mm	mm	mm	mm

