



# Core & Coil (71A) MH ~GT~ 450W

## CORE & COIL HID MH BAL 1000W M141 5-TAP C&C

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

#### **Product data**

General Information	
ANSI Code	M141
Lamp Type	1000W MH
Number of Lamps	1 piece/unit
Circuit Type	SUPER-CWA
Ballast Type	Magnetic HID
Base Model	71A6553
Core Size	4 1/4 x 6 (2 Coil)
Suitable For Outdoor Use	Yes
Ignitor Catalog Number	LI572-H5
Ignitor Temperature Rating	105°C
Capacitor Value	24 MFD
Capacitor Catalog Number	MD2409000
Capacitor Requirements	480V
Capacitor Temperature Rating	90°C
Capacitor Diameter/Oval	1.75 in
Dimensions	
Capacitor Height	3.9 in
Automatic Restart	No

Operating and Electrical	
Input Voltage	120/208/240/277/480 V
Input Frequency	60 Hz
Inp. Current (Open Circuit)	5.16/4.3/3.09/2.61/1.6 A
Input Current (Starting)	6/2.82/3/2.3/1.53 A
Input Current (Short Circuit)	4.35-6.52/2.16-3.24/2.04-3.06/1.8-2.71/1-1.51 V
Secondary Short Circuit Current	4.97-6.08 A
Constant Wattage Deviation	10%
Ballast Factor (Nom)	1
Power Factor (Nom)	0.96
Nominal Open Circuit Voltage	426 V
Input Current (Operating) (Nom)	9.05/5.6/4.7/4.07/2.36 A A
Input Power (Nom)	1080 W
Rated Lamp Watts	1000 W
Wiring	
Wire Striplength	0.5 mm
Wire Length by Color	12"
Wire Type	Stranded


Datasheet, 2019, February 12 data subject to change

### Core & Coil (71A) MH ~GT~ 450W

Remote Wiring Configuration	Yes
Allowed	
Max Ballast-Lamp Distance Remote	5'
Wiring	
Recommended Fuse Value	22/15/12/10/6 A
Approval and Application	
Open Circuit Voltage Test (Volts)	383-468 V
Approbation Marks	ULR CSA certificate RoHS Compliant
Temperature Marking	D/D/B/B/B
UL Recognized	Yes
Hipot Test (1 Minute)	2000 V
Hipot Test (2 Seconds)	2500 V

UL Insulation Class	H(180°C)
UL Temperature Code	1029D
Product Data	
Order product name	CORE & COIL HID MH BAL 1000W M141 5-TAP C&C
EAN/UPC - Product	781087073346
Order code	71A6553500
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	2
Material Nr. (12NC)	913710668402
Net Weight (Piece)	10.719 kg

#### Dimensional drawing



MH BAL 1000W M141 5-TAP C&C





© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.