PHILIPS Lighting



Reflector Infrared R40

250R40 IR/HR/TG 120V 4/1

Philips Family of Specialty Incandescents provide the perfect light for dramatic accents and display lighting as well as general lighting in a variety of applications. Philips Infrared lamps are suited for heating and drying in industrial and commercial applications. These incandescent, gas-filled infrared heat lamps come up to full temperature almost immediately, eliminating costly warm-up time. Highly efficient heat generators produce a minimum of light rays and a high amount of infrared radiation. The BR40 lamp provides a built-in reflector for radiant energy control.


Product data

General Information		
Cap-Base	E26 [Single Contact Medium Screw]	
Operating Position	UNIVERSAL [Any or Universal (U)]	
Rated Lifetime (Hours)	5,000 hour(s)	
Lighting Technology	Incandescent	
Operating and Electrical		
Power Consumption	250 W	
Voltage (Nom)	120 V	
Voltage (Nom)	120 V	
Mechanical and Housing		
Bulb Finish	Red	
Bulb Material	Hard Glass	
Bulb Shape	R40 (R40)	

Approval and Application	
Approval Marks	Circle E logo
Product Data	
Order product name	250R40 IR/HR/TG 120V 4/1
Full product name	250R40 IR/HR/TG 120V 4/1
Order code	925272736308
Material Nr. (12NC)	925272736308
Numerator - Quantity Per Pack	1
EAN/UPC - Product/Case	046677159320
Numerator - Packs per outer box	4
EAN/UPC - Case	50046677159325

Reflector Infrared R40

Dimensional drawing



Product	C (max)
250R40 IR/HR/TG 120V 4/1	6.875 inch



© 2024 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.

www.lighting.philips.com 2024, January 3 - data subject to change