

Reliable performance

Core & Coil (71A) HPS ~GT~ 400W

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Benefits

- Vacuum-pressure impregnation is used to re-enforce the electrical insulation of the ballast, preclude moisture, inhibit noise, and dissipate heat
- Pre-insulated voltage leads reduce the risk of shock and shrink installation time

Features

- Vacuum-pressure impregnated with a silica-filled polyester varnish
- All core and coil ballasts below 600W utilize a UL Class H (180°C) insulation system
- C and C ballasts 600W and higher utilize a UL Class N (200°C) insulation system
- Pre-insulated voltage leads
- Ballast kits supplied with pre-wired ignitor

Application

- High bay retail, manufacturing, gymnasiums, warehouses, parking structures, outdoor


Core & Coil (71A) HPS ~GT~ 400W

Versions



71A8793500

Dimensional drawing



Product	C1	C2	A1	A2	A3	B1	B2
CORE & COIL HID 71A8743600T	5.90 in	3.90 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A8753001	6 in	3.97 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A85F5500D	4.9 in	3.12 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A85E5500D	5.10 in	3.15 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID HPS BAL 1000W S52 480V C&C	5.90 in	3.90 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A8743001	5.90 in	3.90 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A86F5500D	5.13 in	3.12 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A87A3001	5.9 in	3.90 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A8773001	5.75 in	3.75 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID 71A8793600	5.75 in	3.75 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in
CORE & COIL HID HPS BAL 1000W S52 QUAD C&C	5.75 in	3.75 in	6 in	5.4 in	4.4 in	4.3 in	3.9 in

Operating and Electrical	
Input Frequency	60 Hz
General Information	
Number Of Lamps	1 piece/unit

Operating and Electrical

Order Code	Full Product Name	Input Voltage
913700500809	CORE & COIL HID HPS BAL 1000W S52 QUAD C&C	120/208/240/277 V
913700506131	CORE & COIL HID HPS BAL 1000W S52 QUAD C&C	120/208/240/277 V
913700526809	CORE & COIL HID HPS BAL 1000W S52 QUAD KIT	120/208/240/277 V
913700526909	CORE & COIL HID HPS BAL 1000W S52 120/277/347V KIT	120/277/347 V
913700540009	CORE & COIL HID HPS BAL 750W S111 277/347/480V C&C	277/347/480 V

Order Code	Full Product Name	Input Voltage
913700540109	CORE & COIL HID HPS BAL 1000W S52 480V KIT	480 V
913700566109	CORE & COIL HID HPS BAL 1000W S52 480V C&C	480 V
913700578109	CORE & COIL HID HPS BAL 600W S106 120/208/240V C&C	120/208/240 V
913700578309	CORE & COIL HID HPS BAL 600W S106 277/347/480V C&C	277/347/480 V
913710405501	CORE & COIL HID HPS BAL 1000W S52 5-TAP KIT	120/208/240/277/480 V

Core & Coil (71A) HPS ~GT~ 400W

Order Code	Full Product Name	Input Voltage
913710555602	CORE & COIL HID HPS BAL 1000W S52 480V/120T C&C	480/120T V

General Information

Order Code	Full Product Name	Capacitor	
		Value	Lamp Type
913700500809	CORE & COIL HID HPS BAL 1000W S52 QUAD C&C	26 MFD	1000W HPS
913700506131	CORE & COIL HID HPS BAL 1000W S52 QUAD C&C	26 MFD	1000W HPS
913700526809	CORE & COIL HID HPS BAL 1000W S52 QUAD KIT	26 MFD	1000W HPS
913700526909	CORE & COIL HID HPS BAL 1000W S52 120/277/347V KIT	26 MFD	1000W HPS
913700540009	CORE & COIL HID HPS BAL 750W S111 277/347/480V C&C	75 MFD	750W HPS
913700540109	CORE & COIL HID HPS BAL 1000W S52 480V KIT	26 MFD	1000W HPS

Order Code	Full Product Name	Capacitor	
		Value	Lamp Type
913700566109	CORE & COIL HID HPS BAL 1000W S52 480V C&C	26 MFD	1000W HPS
913700578109	CORE & COIL HID HPS BAL 600W S106 120/208/240V C&C	64 MFD	600W HPS
913700578309	CORE & COIL HID HPS BAL 600W S106 277/347/480V C&C	64 MFD	600W HPS
913710405501	CORE & COIL HID HPS BAL 1000W S52 5-TAP KIT	26 MFD	1000W HPS
913710555602	CORE & COIL HID HPS BAL 1000W S52 480V/120T C&C	26 MFD	1000W HPS

