



## Faze 180 Concealed Emergency Unit

## FX12L40W20

Concealed Emergency Unit, Lead Acid, 12V 40W, No Remote, 20W MR16, Xtest

The Faze 180 Series combines aesthetic appeal and architectural excellence. Designed to be the invisible emergency lighting unit utilizing a normal utility power circuit, so it can be controlled by a standard wall switch. With a superior mechanical design and unmatched electronics the Faze 180 is ideal for any design requiring a concealed lighting unit.

## **Product data**

General Information	
Lamp Source Code	Incandescent
Lamp Watts	20
Number of Lamps	2
Operating and Electrical	
Voltages	120/277 V
Maximum Lamp Watts	20
Product Data	
Order product name	FX12L40W20
EAN/UPC - Product	781370853723

Order code	912400372494
Local order code	
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box 1	
Material Nr. (12NC)	912400372494
Net Weight (Piece)	9.000 kg
Commercial Code	FX12L40W20
Catalog Number Description	Concealed Emergency Unit, Lead Acid, 12V 40W, No
	Remote, 20W MR16, Xtest
Quick Ship	-

Datasheet, 2018, July 24 data subject to change