



Faze 180 Concealed Emergency Unit

FX12L70W20

Concealed Emergency Unit, Lead Acid, 12V 70W, 30W Remote, 20W MR16, Xtest

The Faze 180 Series combines aesthetic appeal and architectural excellence. Designed to be the invisible emergency lighting unit utilizing a normal utility power circuit, so it can be controlled by a standard wall switch. With a superior mechanical design and unmatched electronics the Faze 180 is ideal for any design requiring a concealed lighting unit.

Product data

| General Information | |
|--------------------------|--------------|
| Lamp Source Code | Incandescent |
| Lamp Watts | 20 |
| Number of Lamps | 2 |
| | |
| Operating and Electrical | |
| Voltages | 120/277 V |
| Maximum Lamp Watts | 20 |
| | |
| Product Data | |
| Order product name | FX12L70W20 |
| EAN/UPC - Product | 781370853747 |
| | |

| Order code | 912400372495 |
|-----------------------------------|---|
| Local order code | |
| Numerator - Quantity Per Pack | 1 |
| Numerator - Packs per outer box 1 | |
| Material Nr. (12NC) | 912400372495 |
| Net Weight (Piece) | 6.300 kg |
| Commercial Code | FX12L70W20 |
| Catalog Number Description | Concealed Emergency Unit, Lead Acid, 12V 70W, 30W |
| | Remote, 20W MR16, Xtest |
| Quick Ship | - |

Datasheet, 2018, July 24 data subject to change