



Faze 180 Concealed Emergency Unit

Concealed Emergency Unit, Lead Acid, 12V 150W, No Remote, 75W MR16, Xtest

Concealed Emergency Unit, Lead Acid, 12V 150W, No Remote, 75W MR16, Xtest

The Faze 180 Series combines aesthetic appeal and architectural excellence. Designed to be the invisible emergency lighting unit utilizing a normal utility power circuit, so it can be controlled by a standard wall switch. With a superior mechanical design and unmatched electronics the Faze 180 is ideal for any design requiring a concealed lighting unit.

Product data

General Information		EAN/UPC - Product 782343258415	
Lamp Source Code	Incandescent	Order code	FX12L150W75
Lamp Watts	75	Numerator - Quantity Per Pack	1
Number of Lamps	2	Numerator - Packs per outer box	1
Operating and Electrical		Material Nr. (12NC)	912400390350
Voltages	120/277 V	Net Weight (Piece)	0.001 kg
Maximum Lamp Watts	75	Catalog Number	FX12L150W75
Product Data		Catalog Number Description	Concealed Emergency Unit, Lead Acid, 12V 150W, No Remote, 75W MR16, Xtest
Order product name	FX12L150W75		