



LytePro LED Flood Small LPF2

STK- LPF2-E-4K-FL-K-8-BZ

Stock LPF2, 4000K, Flood, Knuckle Mount, 120-277V, Textured Dark Bronze - 87 lm/W

The Philips Keene LytePro LED Small Floodlight allows precision and flexibility in a compact design. The LPF2 features state-of-the-art long-life LED technology and is ideal for landscapes, accenting signage or displays, facades, and many other lighting applications.

Product data

| General Information | | IP Rating | IP66 | |
|-------------------------------|-------------------|---------------------------------|-------------------------------------|--|
| Lamp Source Code | LED | | | |
| Color Temperature | 4000K | Initial Performance (IEC Co | Initial Performance (IEC Compliant) | |
| CRI | 80 | Luminaire Lumens | 3460 | |
| Photometric Distribution Type | NEMA 6H x 6V | Efficacy | 87 lm/W | |
| Mounting | NPT/NPS | | | |
| | | Product Data | | |
| Operating and Electrical | | Order product name | STK- LPF2-E-4K-FL-K-8-BZ | |
| Voltages | 120/208/240/277 V | EAN/UPC - Product | 190096001583 | |
| Luminaire Input Watts | 40 | Order code | STKLPF2K-8 | |
| | | Local order code | | |
| Mechanical and Housing | | Numerator - Quantity Per Pack | 1 | |
| Material | Aluminum | Numerator - Packs per outer box | Numerator - Packs per outer box 4 | |
| | | Material Nr. (12NC) | 912401050214 | |
| Approval and Application | | Net Weight (Piece) | 0.001 kg | |
| Safety Listing | UL | Commercial Code | STKLPF2K-8 | |

LytePro LED Flood Small LPF2

| Catalog Number Description | Stock LPF2, 4000K, Flood, Knuckle Mount, 120-277V, | |
|----------------------------|--|--|
| | Textured Dark Bronze | |
| Quick Ship | Service Smart (2 Days) USA | |



© 2018 Philips Lighting Holding B.V. All rights reserved. Philips Lighting reserves the right to make changes in specifications and/or to discontinue any product at any timewithout notice or obligation and will not be liable for any consequences resulting from the use of this publication.

www.lighting.philips.com 2018, July 23 - data subject to change