PHILIPS

Lighting



Standard

STANDARD MAG BALLAST (1) FC8T9 & (1) FC12T9 120V

Available for many fluorescent lamp types sold today, including Preheat, Rapid Start, 2-pin CFL, Slimline, High Output, Very High Output and Circline. Magnetic ballasts can be used in any application where these lamps are used.

Product data

General Information	
Lamp Type	FC8T9 & FC12T9
Number of Lamps	2 piece/unit
Lamp Footage	-
Ballast Type	Magnetic Fluorescent
Base Model	RS2232TPW
Suitable For Outdoor Use	Yes
Automatic Restart	Yes

Operating and Electrical	
Input Voltage	120 V
Input Frequency	60 Hz
Max THD	15 %
Starting Method	Rapid Start
Lamp Current Crest Factor (Nom)	1.7
Ignition Time (Nom)	1 s
Ballast Factor (Nom)	0.7
Power Factor (Nom)	0.97
Input Current (Operating) (Nom)	0.4 A
Input Power (Nom)	46 W
Rated Lamp Watts	22 & 32 W

Wiring	
Wire Striplength	0.50/0.375 mm
Lamp Connection	Series
Wire Length by Color	See data sheet
Wire Gauge (Nom)	18AWG mm
Wire Type	Solid
Remote Wiring Configuration Allowed	Yes
Tandem Wiring Configuration Allowed	No
Through Wiring Configuration Allowed	No
Max Ballast-Lamp Distance Remote Wiring	30'
Max Ballast-Lamp Distance Tandem Wiring	-
Max Ballast-Lamp Distance Through Wiring	-

Mechanical and Housing	
Housing Material	Metal
Housing	T1
Housing Dimensions	6.5" x 2.38" x 1.5"

Approval and Application	
EMC Immunity Standard	FCC Non-Consumer
Approbation Marks	CSA certificate UL certificate RoHS Compliant
Sound Rating	A

Standard


UL Recognized	No

Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	10
Material Nr. (12NC)	913700501131
Net Weight (Piece)	1.139 kg

Product Data

Order product name	STANDARD MAG BALLAST (1) FC8T9 & (1) FC12T9 120V
EAN/UPC - Product	781087043240
Order code	RS2232TPWI

Dimensional drawing



MAG BALLAST (1) FC8T9 & (1) FC12T9 120V

Product	A1	A2	B1	C1
STANDARD MAG BALLAST (1) FC8T9 & (1) FC12T9 120V	6.5 in	6 in	2.38 in	1.5 in

© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.