PHILIPS Lighting



Core & Coil (71A) MH ~LT~ 175W

CORE & COIL HID MH BAL 35/39W M130 277V C&C

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

General Information				
ANSI Code	M130			
Lamp Type	35/39W MH			
Number of Lamps	1 piece/unit			
Circuit Type	R-HPF			
Ballast Type	Magnetic HID			
Base Model	71A5037P			
Core Size	2 5/8 x 2 3/16			
Suitable For Outdoor Use	Yes			
Ignitor Catalog Number	LI533-H4			
Ignitor Temperature Rating	105°C			
Capacitor Value	5 MFD			
Capacitor Catalog Number	7C050L30RA			
Capacitor Requirements	280V			
Capacitor Temperature Rating	105°C			
Capacitor Diameter/Oval Dimensions	1.25 in			
Capacitor Height	2.9 in			
Automatic Restart	No			


Operating and Electrical				
Input Voltage	277 V			
Input Frequency	60 Hz			
Inp. Current (Open Circuit)	0.52 A			
Input Current (Starting)	0.3 A			
Input Current (Short Circuit)	0.14-0.2 A			
Secondary Short Circuit Current	0.55-0.85 A			
Constant Wattage Deviation	10%			
Ballast Factor (Nom)	1			
Power Factor (Nom)	0.90			
Nominal Open Circuit Voltage	277 V			
Input Current (Operating) (Nom)	0.18 A A			
Input Power (Nom)	48 W			
Rated Lamp Watts	35/39 W			
Wiring				
Wire Striplength	0.5 mm			
Wire Length by Color	12"			
Wire Type	Stranded			
Remote Wiring Configuration Allowed	Yes			

Core & Coil (71A) MH ~LT~ 175W

Max Ballast-Lamp Distance Remote Wiring	7'				
Recommended Fuse Value	2 A				
Approval and Application					
Open Circuit Voltage Test (Volts)	260-290 V				
Approbation Marks	ULR CSA certificate RoHS Compliant				
Temperature Marking	A				
UL Recognized	Yes				
Hipot Test (1 Minute)	2000 V				
Hipot Test (2 Seconds)	2500 V				
UL Insulation Class	H(180°C)				
UL Temperature Code	1029A				

Product Data					
Order product name	CORE & COIL HID 71A5037500DP				
EAN/UPC - Product	781087097304				
Order code	71A5037500DP				
Numerator - Quantity Per Pack	1				
Numerator - Packs per outer box	8				
Material Nr. (12NC)	913700529909				
Net Weight (Piece)	0.803 kg				

Dimensional drawing



MH BAL 35/39W M130 277V C&C

Product	C1	C2	A1	A2	B1	B2
CORE & COIL HID 71A5037500DP	1.9 in	0.8 in	2.6 in	2.2 in	2.2 in	1.8 in



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2019, February 12 - data subject to change