

HID-Basic Gearbox system for SON (India)

BSN 250 M361

Impregnated electromagnetic ballasts of copper and steel construction for use in combination with an external ignitor for High-Pressure Sodium Vapor (SON) lamps

Product data

General Information	
Application Code	250 M361
Lamp Type	SON
Number of Lamps	1 piece/unit
Operating and Electrical	
Input Voltage	220/240 V
Input Frequency	50 Hz
Mains Voltage Performance (AC)	240+6%--8%
Mains Voltage Safety (AC)	240-10%--10%
Input Current with PF Correction	1.30 A
Input Current without PF Correction	3.00 A
Power Factor with PF Compensation	0.85
Power Factor without PF Compensation (Nom)	0.40
Power Losses (Nom)	34 W
Wiring	
Connector Type	Screw


System characteristics	
Rated Ballast-Lamp Power	250 W
Temperature	
T-Winding (Max)	130 °C
Delta-T Normal Conditions	75 °C
Approval and Application	
Energy Efficiency Index	Not specified
Product Data	
Full product code	871150088467100
Order product name	BSN 250 M361
EAN/UPC - Product	8711500884671
Order code	913702253722
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	4
Material Nr. (12NC)	913702253722
Net Weight (Piece)	2.800 kg

HID-Basic Gearbox system for SON (India)

Warnings and Safety

- Ballasts are only suitable for use with integrated luminaires

Dimensional drawing



BSN 250 M361

Product	D1	C1	A1	B1	B2
BSN 250 M361	6.3 mm	64.0 mm	143.5 mm	77.5 mm	66.0 mm

