# **PHILIPS** Lighting



# Capacitors for HID lamp circuits

## CA 50FT28

Compensating capacitors are AC capacitors designed for individual correction of the power factor of transformers and magnetic ballasts in discharge lamps (e.g. fluorescent lamps, halogen and metal halide lamps, high-pressure mercury lamps, sodium lamps) in mains with a frequency of 50 or 60Hz. This allows for an improvement of the luminary's power factor to cosµ>0.85


#### **Product data**

Operating and Electrical	
Input Voltage	250 V
Line Frequency	50 to 60 Hz
Input Frequency	50 to 60 Hz
Wiring	
Connector Type Output Termi	inals push in connector or insulated wires or flat quick-
	connector
Temperature	
Ambient temperature range	-40 ℃ to 85 ℃
Mechanical and Housing	
Housing	M8x10
Approval and Application	1
Approval Marks	Conform GB18489-2001 Conform GB/T18504-2001
	CE marking VDE certificate China Quality Certificate
	CB Certificate

Product Data	
Order product name	CA 50FT28
Full product name	CA 50FT28
Full product code	697480505051200
Order code	913710012491
Material Nr. (12NC)	913710012491
Numerator - Quantity Per Pack	1
EAN/UPC - Product/Case	6974805050512
Numerator - Packs per outer box	56
EAN/UPC - Case	6974805050529

### **Capacitors for HID lamp circuits**

#### Dimensional drawing



Product	E1	A1	A2	A3
CA 50FT28	8.0 mm	148.0 mm	132.0 mm	10.0 mm



© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2023, April 15 - data subject to change