



LED Transformer for LED strip

LED Transformer 60W 24VDC

Constant voltage LED transformer for 24VDC LED application, compatible with Philips and other LED strip and offer 24VDC interface to LED application

Product data

| Operating and Electrical Input Voltage 220 to 240 V Line Frequency 50 to 60 Hz Input Frequency 50 to 60 Hz | |
|--|--|
| Line Frequency 50 to 60 Hz Input Frequency 50 to 60 Hz | |
| Input Frequency 50 to 60 Hz | |
| | |
| | |
| Inrush Current Width 0.33 ms | |
| Inrush Current Peak (Max) 28 A | |
| Number of Products on MCB (16A Type B) 13 | |
| (Max) | |
| | |
| Wiring | |
| Connector Type Input Terminals Screw | |
| Color Input Terminals Green | |
| Color Output Terminals Green | |
| Connector Type Output Terminals Screw | |
| Cable Length From Device to Lamp 1.0 m | |
| | |
| Temperature | |
| Ambient temperature range −20 °C to 50 °C | |

| 85 ℃ | | | |
|-----------------------------------|--|--|--|
| | | | |
| | | | |
| CE marking RoHS Compliant CCC | | | |
| certificate SELV ENEC certificate | | | |
| | | | |
| | | | |
| LED Transformer 60W 24VDC | | | |
| LED Transformer 60W 24VDC | | | |
| 697013372909000 | | | |
| 913710032267 | | | |
| 913710032267 | | | |
| 1 | | | |
| 6970133729090 | | | |
| 20 | | | |
| 6970133729106 | | | |
| | | | |

Datasheet, 2023, April 17 data subject to change

LED Transformer for LED strip

Dimensional drawing

| Product | A1 | A2 | B1 | B2 | C1 |
|---------------------------|--------|--------|-------|---------|-------|
| LED Transformer 60W 24VDC | 180 mm | 170 mm | 52 mm | 42.0 mm | 30 mm |

