



# BPL EM ballasts for CFL, PL-T, PL-S and PL-C lamps

# **BPL 13W 220V B2 SC**

This standard, reliable, long-life electromagnetic ballast for compact fluorescent lamps provides excellent performance with 2-pin and 4-pin CFLni lamps.

### **Product data**


Operating and Electrical	
Input Voltage	220 V
Line Frequency	50 Hz
Input Frequency	50 Hz
Wiring	
Connector Type	Screw
Mechanical and Housing	
Housing	L 85x39x28
Approval and Application	
Energy Efficiency Index	B2
Approval Marks	CE marking CCC certificate


Product Data	
Order product name	BPL 13W 220V B2 SC
Full product name	BPL 13W 220V B2 SC
Full product code	871016306590830
Order code	913710121550
Material Nr. (12NC)	913710121550
Numerator - Quantity Per Pack	1
EAN/UPC - Product/Case	8710163150109
Numerator - Packs per outer box	48
EAN/UPC - Case	8710163066080

Datasheet, 2023, April 15 data subject to change

# BPL EM ballasts for CFL, PL-T, PL-S and PL-C lamps

## Dimensional drawing







© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.