



# F-can (72C)

## F-CAN HID MH BAL 100W M90/140 120/277V FCAN

The Philips Advance line of F-can HID ballasts comes in two dual-voltage configurations for the US and Canadian market. Ballasts for these luminaires are most often encased and potted in fluorescent ballast type cans.

#### **Product data**

General Information				
ANSI Code	M90-M140(PULSESTART)			
Lamp Type	100W MH			
Number of Lamps	1 piece/unit			
Circuit Type	HX-HPF			
Ballast Type	Magnetic HID			
Base Model	72C5381			
Suitable For Outdoor Use	Yes			
Ignitor Catalog Number	Inside Can			
Capacitor Catalog Number	Inside Can			
Automatic Restart	No			
Operating and Electrical				
Input Voltage	120/277 V			
Input Frequency	60 Hz			
Inp. Current (Open Circuit)	2.55/1.1 A			
Input Current (Starting)	2.2/0.95 A			
Input Current (Short Circuit)	0.7-1.1/0.3-0.5 A			
Secondary Short Circuit Current	1.3-1.6 A			
Constant Wattage Deviation	12%			
Ballast Factor (Nom)	1			
Power Factor (Nom)	0.90			
Nominal Open Circuit Voltage	277 V			


Input Current (Operating) (Nom)	1.1/0.48 A A				
Input Power (Nom)	125 W				
Rated Lamp Watts	100 W				
Wiring					
Wire Striplength	0.5 mm				
Wire Length by Color	12"				
Wire Type	Stranded				
Remote Wiring Configuration Allowed	Yes				
Max Ballast-Lamp Distance Remote Wiring 5'					
Recommended Fuse Value	6/3 A				
Mechanical and Housing					
Housing Material	Metal				
Housing	F-Can				
Housing Dimensions	11.75 x 2.63 x 3.19				
Approval and Application					
Open Circuit Voltage Test (Volts)	250-305 V				
Approbation Marks	CSA certificate UL certificate RoHS				
	Compliant				
Temperature Marking	90ºC max. case				
UL Recognized	No				

## F-can (72C)

1600 V				
2000 V				
A(105°C)				
NA				
F-CAN HID MH BAL 100W M90/140				
120/277V FCAN				

EAN/UPC - Product	781087025277
Order code	72C5381NP001
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	1
Material Nr. (12NC)	913710408101
Net Weight (Piece)	4.541 kg

### Dimensional drawing



Product	A1	A2	A3	B1	B2	C1	D1
F-CAN HID MH BAL 100W	12 in	11.13 in	10.5 in	3.9 in	2.0 in	2.6 in	0.3 in
M90/140 120/277V FCAN							

MH BAL 100W M90/140 120/277V FCAN



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2019, March 22 - data subject to change