



Transformers

AUTO-TRANSFORMER AUTOXFMR 277:115 150VA C&C

Stepdown transformers and autotransformers are used when you need to connect a lower voltage device to a higher voltage source.

Product data

General Information			
Circuit Type	Transformer		
Ballast Type	Magnetic HID		
Base Model	71A9749		
Core Size	7/8" E/I		
Suitable For Outdoor Use	Yes		
Operating and Electrical			
Input Voltage	277:120 V		
Input Frequency	60 Hz		
Input Current (Nom)	0.6 A		
Rated Lamp Power	150 VA load W		
Wiring			
Wire Striplength	0.5 mm		
Wire Length by Color	12"		
Wire Type	Stranded		
Remote Wiring Configuration Allowed Yes			
Mechanical and Housing			


NA

Housing Dimensions	NA				
Approval and Application					
Approval Marks	ULR RoHS Compliant				
Temperature Marking	NA				
UL Recognized	Yes				
UL Insulation Class	H(180°C)				
UL Temperature Code	NA				
Product Data					
Order product name	AUTO-TRANSFORMER AUTOXFMR 277:115 150VA				
	C&C				
EAN/UPC - Product	781087974964				
Order code	913710447602				
Numerator - Quantity Per Pack	1				
Numerator - Packs per outer box	24				
Material Nr. (12NC)	913710447602				
Net Weight (Piece)	1.012 kg				

Housing

Transformers

Dimensional drawing



Product	C1	C2	A1	A2	B1	B2
AUTO-TRANSFORMER 71A9749600	2.7 in	1.5 in	2.6 in	2.2 in	2.2 in	1.8 in

AUTO-TRANSFORMER 71A9749600



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.