



Transformers

AUTO-TRANSFORMER AUTOXFMR 480:277 350VA C&C

Stepdown transformers and autotransformers are used when you need to connect a lower voltage device to a higher voltage source.


Product data

General Information	
Circuit Type	Transformer
Ballast Type	Magnetic HID
Base Model	71A9843
Core Size	7/8" E/I
Suitable For Outdoor Use	Yes
Operating and Electrical	
Input Voltage	347:190 or 480:270 V
Input Frequency	60 Hz
Input Current (Nom)	1 A
Rated Lamp Power	350 VA load W
Wiring	
Wire Striplength	0.5 mm
Wire Length by Color	12"
Wire Type	Stranded
Remote Wiring Configuration Allowed Yes	
Mechanical and Housing	
Housing	NA

Housing Dimensions	NA
Approval and Application	
Approval Marks	ULR CSA certificate RoHS Compliant
Temperature Marking	NA
UL Recognized	Yes
UL Insulation Class	H(180°C)
UL Temperature Code	NA
Product Data	
Order product name	AUTO-TRANSFORMER AUTOXFMR 480:277
	350VA C&C
EAN/UPC - Product	781087069110
Order code	199687
Local order code	199687
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	12
Material Nr. (12NC)	913710663402
Net Weight (Piece)	1.665 kg

Transformers

Dimensional drawing



 Product
 C1
 C2
 A1
 A2
 B1
 B2

 AUTO-TRANSFORMER AUTOXFMR
 3.6 in
 2.35 in
 2.6 in
 2.2 in
 2.2 in
 1.8 in

 480:277 350VA C&C
 500 V
 500 V
 500 V
 500 V
 500 V
 500 V

AUTO-TRANSFORMER 71A9843600



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2019, March 22 - data subject to change