



# Core & Coil (71A) MH 175W - 450W

## **CORE & COIL HID 71A6343500DTEE**

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

#### **Product data**

General Information	
ANSI Code	M144
Lamp Type	450W MH
Number of Lamps	1 piece/unit
Circuit Type	SUPER-CWA
Ballast Type	Magnetic HID
Base Model	71A6343TEE
Core Size	4 1/4 x 4 3/4 (2 coil)
Suitable For Outdoor Use	Yes
Ignitor Catalog Number	LI533-H4
Ignitor Temperature Rating	105°C
Capacitor Value	26.5 MFD
Capacitor Catalog Number	7C265P40R
Capacitor Requirements	360V
Capacitor Temperature Rating	105°C
Capacitor Diameter/Oval Dimensions	1.75 in
Capacitor Height	4.80 in
Automatic Restart	No
Operating and Electrical	
Input Voltage	480/120T V
·	·

Input Frequency	60 Hz
Input Current (Open Circuit)	0.7 A
Input Current (Starting)	0.65 A
Input Current (Short Circuit)	0.5-0.75 A
Secondary Short Circuit Current	3.85-4.75 A
Constant Wattage Deviation	10%
Ballast Factor (Nom)	1
Power Factor (Nom)	0.90
Open Circuit Voltage	267 V
Input Current (Nom)	1.1 A A
Input Power (Nom)	514 W
Rated Lamp Power	450 W
Wiring	
Wire Striplength	0.5 mm
Wire Length by Color	12"
Wire Type	Stranded
Remote Wiring Configuration Allowed	Yes
Max Ballast-Lamp Distance Remote Wiring	5'
Recommended Fuse Value	3 A


Datasheet, 2019, February 12 data subject to change

# Core & Coil (71A) MH 175W - 450W

240-295 V
ULR CSA certificate EISA RoHS Compliant
D
Yes
2000 V
2500 V
H(180°C)
1029D

Product Data	
Order product name	CORE & COIL HID 71A6343500DTEE
EAN/UPC - Product	781087077634
Order code	913710699002
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	4
Material Nr. (12NC)	913710699002
Net Weight (Piece)	6.564 kg

## Dimensional drawing



MH BAL 450W M144 480V/120T C&C

