



Safety & Comfort Starters

S2E 18-22W SER 220-240V BL 1BC/10

Range of premium quality electronic starters for igniting fluorescent lamps operating on conventional electromagnetic ballast.


Product data

| | |
|--------------------------|-----------------------------------|
| Operating and Electrical | |
| Power Consumption | 18 22 W |
| Voltage (Nom) | 220-240 V |
| Mechanical and Housing | |
| Housing Color | Blue |
| Product Data | |
| Order product name | S2E 18-22W SER 220-240V BL 1BC/10 |
| Full product name | S2E 18-22W SER 220-240V BL 1BC/10 |

| | |
|---------------------------------|-----------------|
| Full product code | 871150069841425 |
| Order code | 928392600387 |
| Material Nr. (12NC) | 928392600387 |
| Numerator - Quantity Per Pack | 1 |
| EAN/UPC - Product/Case | 8711500698414 |
| Numerator - Packs per outer box | 10 |
| EAN/UPC - Case | 8711500698421 |

Safety & Comfort Starters

Dimensional drawing



| Product | C (max) | E (max) |
|-----------------------------------|---------|---------|
| S2E 18-22W SER 220-240V BL 1BC/10 | 40.3 mm | 21.5 mm |

