



Tornado High Lumen

Tornado High Lumen 60W CDL E27 1CT/6

Energy saving lamp in spiral shape, with superior performance (long life, high switching) and high lumen warm bright light. Perfectly suitable to be used in places where high lumen is required, and the lamp is directly visible.

Product data


| General Information | | Warm Up Time to 60% Light (Max) | |
|---------------------------------------|---------------------|---------------------------------|--------------------------------------|
| Cap-Base | E27 [E27] | | 60 s |
| Nominal Lifetime (Nom) | 10000 h | Power Factor (Nom) | 0.92 |
| Switching Cycle | 10000X | Voltage (Nom) | 220-240 V |
| Light Technical | | Controls and Dimming | |
| Colour Code | 865 [CCT of 6500K] | Dimmable | No |
| Luminous Flux (Nom) | 4300 lm | Approval and Application | |
| Luminous Flux (Rated) (Nom) | 4300 lm | Energy Efficiency Label | A |
| Colour Designation | Cool Daylight | Mercury (Hg) Content (Max) | 5 mg |
| Lumen Maintenance 2000 h (Nom) | 88 % | Energy Consumption kWh/1000 h | 60 kWh |
| Chromaticity Coordinate X (Nom) | 313 | Product Data | |
| Chromaticity Coordinate Y (Nom) | 337 | Full product code | 872790080721900 |
| Colour Temperature, horizontal (Nom) | 6500 K | Order product name | Tornado High Lumen 60W CDL E27 1CT/6 |
| Luminous Efficacy (rated) (Nom) | 71.63 lm/W | EAN/UPC - Product | 8727900807219 |
| Colour Rendering Index horiz (Nom) | 80 | Order code | 80721900 |
| LLMF At End Of Nominal Lifetime (Nom) | 60 % | Numerator - Quantity Per Pack | 1 |
| Operating and Electrical | | Numerator - Packs per outer box | 6 |
| Input Frequency | 50 or 60 Hz | Material Nr. (12NC) | 929676006201 |
| Power (Rated) (Nom) | 60.0 W | Net Weight (Piece) | 0.300 kg |
| Lamp Current (Nom) | 270 mA | | |
| Starting Time (Nom) | 1.5 s | | |

Tornado High Lumen

Warnings and Safety

- Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.
- Compact fluorescent lamps have to be treated as special waste, they must be taken to your local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass etc.

Dimensional drawing



| Product | C (max) | F (max) | D (max) |
|--------------------------------------|---------|---------|---------|
| Tornado High Lumen 60W CDL E27 1CT/6 | 262 mm | 88.1 mm | 102 mm |

HL HS HV 10Kh EMI HPF 65W 220-240VE27CDL

