



Tornado T3

Tornado T3 32W WW E27 220-240V 1PF/6

Energy-saving lamp in a decorative, spiral shape

Product data

General Information	
Cap-Base	E27 [E27]
Switching Cycle	8000X
Light Technical	
Colour Code	827 [CCT of 2700K]
Luminous Flux (Nom)	2255 lm
Luminous Flux (Rated) (Nom)	2255 lm
Colour Designation	Warm White (WW)
Lumen Maintenance 2000 h (Nom)	88 %
Chromaticity Coordinate X (Nom)	463
Chromaticity Coordinate Y (Nom)	420
Colour Temperature, horizontal (Nom)	2700 K
Colour Rendering Index horiz (Nom)	80
Operating and Electrical	
Input Frequency	50 or 60 Hz
Power (Rated) (Nom)	32.0 W
Lamp Current (Nom)	140 mA
Wattage Equivalent	150 W
Starting Time (Nom)	0.3 s
Warm Up Time to 60% Light (Min)	5 s
Warm Up Time to 60% Light (Max)	40 s

Power Factor (Nom)	0.95
Voltage (Nom)	220-240 V

Controls and Dimming	
Dimmable	No

Approval and Application	
Energy Efficiency Label	A
Mercury (Hg) Content (Max)	2.5 mg
Mercury (Hg) Content (Nom)	2 mg
Energy Consumption kWh/1000 h	32 kWh


Product Data	
Full product code	872790087628400
Order product name	Tornado T3 32W WW E27 220-240V 1PF/6
EAN/UPC - Product	8727900876284
Order code	87628400
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	6
Material Nr. (12NC)	929689301301
Net Weight (Piece)	0.105 kg

Tornado T3

Warnings and Safety

- Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.
- Compact fluorescent lamps have to be treated as special waste, they must be taken to your local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass etc.

Dimensional drawing



Product	C (max)	D (max)	F (max)
Tornado T3 32W WW E27 220-240V 1PF/6	152.5 mm	74 mm	61 mm

High Lumen QFS HPF 32W E27 2700K

